



US006618631B1

(12) **United States Patent**
Johnson et al.

(10) **Patent No.:** **US 6,618,631 B1**
(45) **Date of Patent:** **Sep. 9, 2003**

(54) **ADAPTIVE CONTROL SYSTEM HAVING HEDGE UNIT AND RELATED APPARATUS AND METHODS**

(75) Inventors: **Eric Norman Johnson**, Atlanta, GA (US); **Anthony J. Calise**, Atlanta, GA (US)

(73) Assignee: **Georgia Tech Research Corporation**, Atlanta, GA (US)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.

(21) Appl. No.: **09/585,106**

(22) Filed: **May 31, 2000**

Related U.S. Application Data

(60) Provisional application No. 60/199,615, filed on Apr. 25, 2000.

(51) **Int. Cl.**⁷ **G05B 13/02**

(52) **U.S. Cl.** **700/28; 700/29; 700/30; 700/31; 700/32; 700/47; 700/48; 700/173; 701/58; 701/59; 701/60; 701/63; 701/68**

(58) **Field of Search** **700/28, 29, 30, 700/31, 32, 47, 48, 173; 701/58, 59, 60, 63, 68**

(56) **References Cited**

U.S. PATENT DOCUMENTS

4,062,508 A	12/1977	Stephens et al.	244/83
4,466,054 A	8/1984	Shigemasa et al.	364/162
5,113,483 A	5/1992	Keeler et al.	395/23
5,155,802 A	10/1992	Mueller et al.	395/24
5,170,463 A	12/1992	Fujimoto et al.	395/11
5,224,664 A	7/1993	Adams, Sr. et al.	
5,241,509 A	8/1993	Jousselin et al.	365/230.01
5,253,328 A	10/1993	Hartman	395/24
5,268,834 A *	12/1993	Sanner et al.	700/31
5,274,746 A	12/1993	Mashiko	395/27
5,282,261 A	1/1994	Skeirik	395/22
5,303,385 A	4/1994	Hattori et al.	395/22
5,311,421 A	5/1994	Nomura et al.	364/157
5,313,559 A	5/1994	Ogata et al.	395/23
5,367,612 A	11/1994	Bozich et al.	395/22

5,396,415 A	3/1995	Konar et al.	364/162
5,406,474 A *	4/1995	Hansen	700/37
5,469,265 A	11/1995	Measures et al.	356/419
5,475,793 A	12/1995	Broomhead et al.	395/2
5,541,843 A	7/1996	Yamaguchi et al. ...	364/426.02
5,682,309 A	10/1997	Bartusiak et al.	
5,687,075 A *	11/1997	Stothers	700/28
5,691,893 A *	11/1997	Stothers	700/28
5,692,708 A	12/1997	Coleman et al.	
5,768,124 A *	6/1998	Stothers et al.	700/38
5,796,608 A *	8/1998	Bunzemeier	700/37
5,901,059 A *	5/1999	Tao et al.	700/29
5,936,792 A	8/1999	Kobayashi et al.	
6,026,793 A *	2/2000	Yasui et al.	123/674
6,092,919 A *	7/2000	Calise et al.	700/31
6,216,047 B1 *	4/2001	Goto	700/28
6,230,062 B1 *	5/2001	Shah	700/29
6,241,435 B1 *	6/2001	Huang et al.	700/177

OTHER PUBLICATIONS

Patent Cooperation Treaty, International Search Report, Feb. 6, 2002, International Application No. PCT/US01/12797, filed Apr. 20, 2001 by Applicant Georgia Tech Research Corporation.

* cited by examiner

Primary Examiner—John Follansbee


Assistant Examiner—Thomas Pham

(74) *Attorney, Agent, or Firm*—Alston & Bird LLP

(57) **ABSTRACT**

The invention includes an adaptive control system used to control a plant. The adaptive control system includes a hedge unit that receives at least one control signal and a plant state signal. The hedge unit generates a hedge signal based on the control signal, the plant state signal, and a hedge model including a first model having one or more characteristics to which the adaptive control system is not to adapt, and a second model not having the characteristic(s) to which the adaptive control system is not to adapt. The hedge signal is used in the adaptive control system to remove the effect of the characteristic from a signal supplied to an adaptation law unit of the adaptive control system so that the adaptive control system does not adapt to the characteristic in controlling the plant.

32 Claims, 11 Drawing Sheets






FIGURE 2




FIGURE 3







FIGURE 4



10

FIGURE 5








Figure 8




Figure 9

FIGURE 10





FIGURE 11



ADAPTIVE CONTROL SYSTEM HAVING HEDGE UNIT AND RELATED APPARATUS AND METHODS

CROSS-REFERENCE TO RELATED APPLICATION

This application claims priority benefits of provisional application No. 60/199,615 filed Apr. 25, 2000 naming Eric Norman Johnson and Anthony J. Calise as inventors.

STATEMENT OF U.S. GOVERNMENT RIGHTS IN THE INVENTION

This invention was made with U.S. Government funding under Contract No. NAG8-1638 awarded by the National Aeronautics and Space Administration (NASA)-Marshall Space Flight Center and Contract No. F49620-98-1-0437 awarded by the Air Force Office of Scientific Research (AFOSR). The U.S. Government has certain rights in the invention.

FIELD OF THE INVENTION

The invention is directed to an adaptive control system and related method. More particularly, the invention is directed to an adaptive control system with the capability to prevent or reduce undesired adaptation of a control system due to selected characteristic(s) of the plant or control system.

BACKGROUND OF THE INVENTION

Adaptive control systems have the capability to adapt control response to changing conditions within the plant being controlled or the plant's operating environment. Adaptation to changing plant or environmental conditions provides enhanced control response for many kinds of plants, and may be required for certain types of plants that cannot be controlled with static control systems. However, conventional adaptive control systems have a tendency to adapt to plant or control system characteristics to which they should not. The control response of adaptive control systems can be greatly diminished when subjected to certain characteristic(s) of the plant or system, and can be rendered unstable in attempting to adapt to these characteristics. An example of a characteristic that could adversely affect an adaptive control system is a control or authority limit imposed on the control elements of an adaptive control system. If an operator generates a command signal that exceeds the ability of the control system or plant to respond, adaptation of the control system can render the control system unstable. It is desirable to reduce or prevent the impact of such characteristic(s) from adversely affecting the adaptive control system's performance.

SUMMARY OF THE INVENTION

The methods, apparatus, and system, of the invention overcome the disadvantages noted above.

A first method of the invention comprises generating a hedge signal to avoid adaptation to a characteristic of at least one of an adaptive control system and a plant controlled by such system. The first method can comprise modifying a commanded state signal with the hedge signal. The first method can also comprise generating a reference model state signal using the commanded state signal modified by the hedge signal. The first method also can comprise generating a tracking error signal based on the reference model state signal and a plant state signal, and generating an adaptive

control signal to adapt control response of the adaptive control system. Through compensation for the characteristic in the tracking error signal, the adaptive control signal can be generated so as not to significantly adapt to the characteristic. Hence a characteristic of the plant or control system that would impair or be detrimental to control system's performance and/or stability can be hedged out of the adaptive portion of the control system to prevent adverse impact on control of the plant. The hedge signal can be generated based on a difference between a first signal derived from a plant model not having the characteristic to be hedged, and a second signal derived from a plant model having the characteristic. The first signal can be generated based on an input control signal and a plant state signal in addition to the plant model not having the characteristic. The second signal can be generated using a command control signal and a plant state signal, in addition to the plant models with the characteristic. The input control signal can be generated based on a commanded state signal, a plant state signal, and an adaptive control signal, and the command control signal can be generated using the input command signal modified by a control allocation and a control characteristic imposed by a controller. The input control signal and command control signal can be used to hedge a characteristic of the control system to which adaptation is not to be performed. The method can also include generating a display based on the input control signal. An operator can use the display to generate a command control signal. In this aspect of the invention, the operator's control and response can be hedged.

A second method of the invention is executed by an adaptive control system. The second method comprises generating an input control signal based on a commanded state signal, a plant state signal, and an adaptive control signal. The second method also comprises generating a command control signal based on a commanded state signal, a plant state signal, an adaptive control signal, and further based on control allocation and a control characteristic of a controller used to generate the command control signal. The second method further comprises supplying the command control signal to an actuator, controlling a state of the plant based on the command control signal, sensing a state of the plant, and generating a plant state signal based on the sensing of the plant. The second method comprises generating a first signal based on the input control signal, the plant state signal, and a plant model without a plant characteristic to which the adaptive control system is not to adapt. The second method also comprises generating a second signal based on the command control signal, the plant state signal, and a plant model with the plant characteristic to which the adaptive control system is to adapt. The second method further comprises generating a hedge signal by differencing the first and second signals, and generating a reference model state signal by modifying the commanded state signal with the hedge signal to include the effect of the control allocation and control characteristic on plant state from the reference model state signal. The second method further comprises comparing the plant state signal and the reference model state signal, generating a tracking error signal based on the comparing step, and generating the adaptive control signal based on the tracking error signal. The second method can comprise generating a reference model signal based on the commanded state signal, the hedge signal, and a reference model signal derived from a reference model representing the target response of the plant, the reference model signal to generate the input control signal. The second method can also comprise generating a reference model

signal based on the commanded state signal, the hedge signal and a reference model signal derived from a reference model representing the target response of the plant, the reference model signal, to generate the command control signal. The second method can also comprise generating a linear control signal based on the tracking error signal, generating a reference model signal based on the commanded state signal, the hedge signal, and a reference model, and generating a pseudo-control signal based on the linear control signal, the reference model signal, and the adaptive control signal, and the pseudo-control signal. The adaptive control signal can be generated with the plant state signal. The adaptive control signal can be generated with a neural network having connection weights adjusted based on the tracking error signal and the pseudo-control signal. The neural network maps the plant state signal to the adaptive control signal. The plant state signal can also be used to generate the adaptive control signal. The second method can comprise generating the commanded state signal based on a control action from an operator. The operator can be human, and the method can comprise generating a display based on the plant state signal. The display can be used by the operator to generate the commanded state signal. The second method can comprise generating the commanded state signal based on a signal generated by an operator that is a computer. The second method can also comprise generating a display for an operator based on the input control signal so that the operator can generate the command control signal based on the display.

An apparatus of the invention can be used in an adaptive control system for controlling a plant. The apparatus is a hedge unit coupled to receive at least one control signal and a plant state signal. The hedge unit generates a hedge signal based on the control signal, the plant state signal, and a hedge model including a first model having a characteristic to which the adaptive control system is not to adapt, and a second model not having the characteristic to which the adaptive control system is not to adapt. The hedge signal can be used in the adaptive control system to remove the characteristic from a signal supplied to an adaptation law unit of the adaptive control system so that the adaptive control system does not adapt to the characteristic in controlling the plant. The characteristic to be hedged by the hedge unit can be a time delay between generation of the commanded state signal by the controller at a time, and receipt by the controller of the plant state signal resulting from the commanded state signal generated at the time. Also, the characteristic can be a time delay between generation of a state by the plant and sensing of the state of the plant by the sensor to generate the plant state signal. Alternatively, the characteristic can pertain to a control limit of the actuator used to control the plant. The control limit can be due to actuator end points, actuator dynamics, a rate limit of the actuator, or quantization effects associated with the actuator, for example.

An adaptive control system of the invention is coupled to receive a command state signal indicative of a target state of a plant controlled by the adaptive control system. The adaptive control system comprises a controller coupled to receive the commanded state signal, a plant state signal, and an adaptive control signal. The controller generates an input command signal based on the commanded state signal, the plant state signal, the adaptive control signal, and a control model. The controller generates a command control signal based on the commanded state signal, the plant state signal, the adaptive control signal, the control model, control allocation of the controller, and at least one control characteristic

of the controller. The controller is coupled to supply the command control signal to the plant to control the plant's state. The actuator is coupled to receive the command control signal, and affects physical control of the plant's state using the command control signal. The adaptive control system can comprise a sensor coupled to sense the plant state, that generates a plant state signal based on the sensed plant state. The adaptive control system also comprises a hedge unit coupled to receive the input control signal, the command control signal, and the plant state signal. The hedge unit generates a hedge signal to modify the command state signal based on the input control signal, the command control signal, the plant state signal, and a hedge model indicative of a characteristic of at least one of the plant and the adaptive control system, to remove the effect of the characteristic on a tracking error signal. The adaptive control system also comprises a reference model unit coupled to receive the command state signal and the hedge signal. The reference model unit generates a reference model state signal based on the commanded state signal and a hedge signal. The adaptive control unit also comprises a comparator unit coupled to receive the reference model state signal and the plant state signal. The comparator unit generates a tracking error signal based on a difference between the plant state signal and the reference model state signal. The adaptive control system also includes an adaptation law unit coupled to receive the tracking error signal. The adaptive control system generates the adaptive control signal based on the tracking error signal. The adaptation law unit is coupled to supply the adaptive control signal to the controller. The controller can generate the input control signal and the command control signal further based on the reference model state signal. The characteristic to be hedged by the adaptive control system can be time delay between generation of the commanded state signal by the controller at a particular time, and receipt by the controller of the plant state signal resulting from the commanded state signal generated at the particular time. Alternatively, the characteristic can be a time delay between generation of a state by the plant in response to the command control signal, and sensing of the state of the plant resulting from the command control signal. Further, the characteristic can be a control limit of the actuator used to control the plant. The control limit can be due to actuator end points, actuator dynamics, a rate limit of the actuator, or quantization effects of the actuator, for example. The commanded state signal can be generated by an operator, and the adaptive control system can comprise an operator interface unit coupled to receive the plant state signal. The operator interface unit relays the plant state to the operator. The command unit can be used by the operator to generate the command state signal based on the operator's control action. The operator interface can be a display generated based on the plant state signal. The operator can be a human being that generates the control action to the command unit to generate the commanded state signal. The commanded state signal is generated by a machine operator based on the plant state signal. The adaptation law unit can comprise a neural network having connection weights determined by the tracking error signal. The neural network can map the plant state signal to the adaptive control signal based on the connection weights to generate the adaptive control signal. The controller can generate a pseudo-control signal based on the commanded state signal and the plant state signal. The controller can be coupled to supply the pseudo-control signal to the neural network to adjust the connection weights of the neural network. The controller can comprise a dynamic inversion unit to generate the command control signal.

These together with other objects and advantages, which will become subsequently apparent, reside in the details of construction and operation of the invented methods, apparatus, and article as more fully hereinafter described and claimed, reference being made to the accompanying drawings, forming a part hereof, wherein like numerals refer to like parts throughout the several views.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a general block diagram of the adaptive control system of the invention that uses a hedge signal to hedge against a characteristic to which the adaptive control system is not to adapt;

FIG. 2 is a block diagram of a controller of the adaptive control system that generates a command control signal to control an actuator affecting a state of a plant;

FIG. 3 is a block diagram of a hedge unit of the adaptive control system;

FIG. 4 is a block diagram of a reference model unit of the adaptive control system;

FIG. 5 is a view of a processor-based system for implementing the adaptive control system of FIGS. 1-4;

FIG. 6 is a flowchart of a method of the invention used to generate a hedge signal to prevent or reduce adaptation of the adaptive control system of FIGS. 1-4 to the characteristic that is to be hedged;

FIG. 7 is a block diagram of an adaptive control system that includes a neural network for generating an adaptive control signal based on a tracking error signal and a pseudo-control signal;

FIG. 8 is a relatively detailed block diagram of a hedge unit used with the adaptive control system of FIG. 7;

FIG. 9 is a relatively detailed block diagram of a reference model unit used to implement a second-order reference model to generate a target reference model state response to a commanded state signal;

FIG. 10 is a relatively detailed view of a neural network that can be used to map a tracking error signal and a plant state signal to an adaptive control signal using connection weights set adaptively based on a tracking error signal, a pseudo-control signal, and the plant state signal; and

FIG. 11 is a block diagram of a control and allocation and characteristic unit in a special case in which an operator is included in the unit.

DETAILED DESCRIPTION OF THE INVENTION

As used herein, the following terms have the following definitions:

“Actuator” can be virtually any device capable of affecting the state of a plant to control a degree of freedom thereof. Such actuator can be a motor, motor-driven screw, a hydraulic cylinder, a pump or valve controlling a stream of air, a thermal heater, a compressor or suction generator, or other device.

“Adaptive control system” means a control system having the capability to adapt to changes in a controlled plant or its environment over time.

“Characteristic” is a property of a plant or control system that has an effect for which adaptation of the control system is not to be performed. The characteristic can be a time delay between generation of a command signal and sensing and report of the plant state resulting from the command signal to the control system. The char-

acteristic can also be a control limit such as actuator end points, e.g., extreme positions, temperatures, pressures, etc. obtainable by the actuator, actuator dynamics, rate limits, quantization effects, and possibly others. The characteristic can also be a feature of a sensor, for example, the time delay from change of a plant state to sensing of that changed plant state by the sensor. The characteristic can also be an operator’s control or response.

“Control limit” is a limit on the capability of a control system to control a plant. A control limit can also be imposed by limitations in the actuators used to control the plant. These limitations can include actuator end points, e.g., extreme positions, temperatures, pressures, etc. obtainable by the actuator, actuator dynamics, rate limits, quantization effects, and possibly others. Control limits could also be imposed intentionally for a variety of reasons. Adaptive control systems are sensitive to control limits that can cause the adaptive control systems to lose stability. The invention provides the capability to compensate for control limits to permit stable control of the plant with the adaptive control system.

“Hedge” means to reduce or prevent adaptation of an adaptive control system to a characteristic.

“Hedge model” is a model of one or more elements of the system or plant with and without a characteristic that is to be hedged. A hedge model may be a model of a plant, a control system, e.g., an actuator or sensor, an operator, or any other feature of the control system or plant to which the control system is not to adapt.

“Operator” can be a human or computer, for example, that senses a plant state using a plant state signal, and generates a commanded state signal to control the plant.

“Plant” refers to a system controlled by a control system. For example, the plant can be an aircraft, spacecraft, space-launch vehicle, satellite, missile, guided munition, automobile, or other vehicle. The plant can also be a robot, or a pointing or orientation system such as a satellite orientation system to orient power-generation panels, a transceiver, or a docking mechanism. Such plant can also be a braking system, an engine, a transmission, or an active suspension, or other vehicle subsystem. The plant could be a manufacturing facility or a power generation facility. The plant could also be virtually any controllable system.

“Sensor” can be virtually any device(s) for sensing a degree of freedom of a plant’s state, whether alone or in combination with one or more other sensors, to generate a measurement or estimate of plant state. The sensor can be virtually any device suitable for sensing information regarding a plant’s state. For example, the sensor could be a gyroscope for detecting orientation of a vehicle such as an aircraft, i.e., pitch or roll attitudes or side slip. The sensor can also be a temperature or pressure sensor, a position, velocity, or inertial sensor.

“(s)” means one or more of the thing meant by the word preceding “(s)”. Thus, characteristic(s) means one or more characteristics.

The adaptive control system 10 of FIG. 1 operates in a control cycle that is repeatedly executed to control the plant 12 on an ongoing basis, at least until control is terminated. The basic function of the system 10 is to generate a commanded control signal d_{cmd} using a commanded state signal x_r , a plant state signal x_p , an adaptive control signal

v_{ad} , and optionally a reference model state signal x_{rm} . In the case of the first execution of the control cycle, when previous values of the plant state signal x_p and the adaptive control signal v_{ad} are employed, they are assigned predetermined values, respectively. The commanded state signal x_r is used by the controller **14** along with the plant state signal x_p and an adaptive control signal v_{ad} to generate at least one control signal d . If adaptation to one or more characteristics of the controller **14** is to be avoided, the controller **14** is implemented to generate an input control signal d_{in} that is the control signal d generated by the controller **14** before imposition of the characteristic(s) on such control signal, and a command control signal d_{cmd} that is the input control signal d_{in} , modified by the controller's characteristic. The controller **14** is coupled to supply the command control signal d_{cmd} to the actuator **16** that controls the state of the plant **12**. The plant state is sensed by the sensor(s) **18** to generate a plant state signal x_p . The hedge unit **20** is coupled to receive the input control signal d_{in} and the command control signal d_{cmd} for the control cycle under execution from the controller **14**. In addition, the hedge unit **20** is coupled to receive the plant state signal x_p , and optionally the actuator state signal x . The hedge unit **20** uses a plant model to predict the plant states resulting from the input command signal d_{in} and the command control signal d_{cmd} , and generates a hedge signal v_h based on a difference between these two predicted plant states. Therefore, the hedge unit **20** generates the hedge signal v_h to isolate the contribution to plant state that results from the presence of the control characteristic(s) in the command control signal d_{cmd} . In addition, the hedge unit **20** can impose a plant model without one or more plant characteristic(s) for which adaptation is not to be performed by the system **10**, and a plant model that includes the plant characteristic(s). By using the plant model without the plant characteristic to modify the input control signal d_{in} to generate a first signal and by using the plant model with the characteristic(s) to modify the command control signal d_{cmd} to generate a second signal, the hedge unit **20** can generate the hedge signal v_h to isolate the contribution to plant state that results from the presence of the plant characteristic. The hedge unit **20** is coupled to supply the hedge signal v_h to the reference model unit **22**. The reference model unit **22** is also coupled to receive the commanded state signal x_r . The reference model unit **22** uses the hedge signal v_h and a reference model indicating the target state of the plant based on the commanded state, to modify the commanded state signal x_r to include the contribution to plant state caused by the characteristic(s) to be hedged. The comparator **24** is coupled to receive the reference model state signal x_{rm} and the plant state signal x_p , and generates a tracking error signal e . The comparator **24** can generate the tracking error signal e by differencing the plant state signal x_p and the reference model state signal x_{rm} to generate the tracking error signal e . The comparator **24** is coupled to supply the tracking error signal e to the adaptation law unit **26**. Because the characteristic(s) for which no adaptation of control response is to be made has been removed, at least partially, from the tracking error signal e , the adaptation law unit **26** will necessarily not adapt to such characteristic(s). Accordingly, the presence of the characteristic(s) has no impact on performance of the adaptation law unit **26**. The adaptation law unit **26** generates an adaptive control signal v_{ad} based on the tracking error signal e . The adaptation law unit **26** can optionally be coupled to receive the plant state signal x_p as indicated by the broken line in FIG. 1, for use in generating the adaptive control signal v_{ad} . In addition, the adaptation law unit **14** can be

coupled to receive a pseudo-control signal v_{pc} generated by the controller **14** for use by the adaptation law unit **26** in generating the adaptive control signal v_{ad} .

In FIG. 2, the controller **14** includes a control model **140** and a control allocation and characteristic unit **142**. The control model **140** and the control allocation and characteristic unit **142** can be implemented as software modules within the hedge unit **14**. The control model **140** is basically a software implementation of the control law to be implemented by the adaptive control system **10** to control the plant **12**. The control model **140** is coupled to receive either the commanded state signal x_r , or the reference model state signal x_{rm} , and is also coupled receive the plant state signal x_p and the adaptive control signal v_{ad} . The control model **140** maps these signals to the input control signal d_{in} . Those of ordinary skill in the art will understand how to generate a control law appropriate for a plant controlled by the adaptive control system **12**. For example, the control model **140** can be a linear proportional plus derivative, or proportional plus integral control law implemented in a software module or function. The control model **140** is coupled to supply the input control signal d_{in} to the control allocation and characteristic unit **142**. The unit **142** maps the input control signal d_{in} to the control signal d_{cmd} . The unit **142** can map the input control signal d_{in} to the control signal d_{cmd} so as to allocate control responsibility for the plant's controlled degree of freedom based on a predetermined scheme. For example, the plant **12** could be an aircraft configured so the ailerons on both wings can be controlled to achieve a commanded roll attitude. The unit **142** can serve to allocate the amount of aileron deflection to the two actuators that control the wing ailerons so as to influence the roll attitude commanded by the input control signal d_{in} . The unit **142** can include the on-line identification of a model of the plant and the optimal or near-optimal allocation of multiply-redundant control effectors based on the solution of an optimization scheme that employs either the identified plant model or a stored model of the plant. The unit **142** can also impart control characteristic(s) to the input control signal d_{in} to generate the control signal d_{cmd} . Such control characteristic (s) could be control limits such as actuator end points that cannot be exceeded due to limitations of the actuator or associated control linkages. Alternatively, the control characteristic(s) could be conservative authority limits placed on the control signal d_{in} , to insure the actuator end points are never encountered. For example, the actuator may be capable of moving a control surface by ± 21 degrees of angle. If the input control signal d_{in} designates 25 degrees of angle, the unit **142** will clip the input control limit d_{in} to produce a command control signal of 20 degrees of angle. Another control limit may pertain to an actuator's rate limit. It is possible that the input command signal d_{in} may command the actuator **16** to respond more rapidly than it is able. Accordingly, the unit **142** can be programmed to generate the command control signal d_{cmd} to move the actuator **16** more gradually as compared to the input control signal d_{in} . As another example, the actuator **16** may be able to move only in quantized steps. The unit **142** can be used to map the control signal d_{in} to the command control signal d_{cmd} so that the command control signal is quantized. In addition, the unit **142** can be used to impose authority limits on the actuator **16**. Thus, although an actuator **16** can be capable of actuation to the point of endangering the plant, the unit **142** can be used to impose a control limit on the actuator **16**. Therefore, for example, if the operator **30** is an auto-pilot monitored by a human pilot to take control in emergency situations, the auto-pilot can be limited to control

the aircraft plant 12 to limits set by the unit 142. Control limits set by the unit 142 can also be imposed by the sensor 18. For example, if the actuator 16 can change the state of the plant 12 faster than the sensor 18 can sense the resulting changes, the unit 142 can limit the input control signal d_{in} to generate the command control signal d_{cmd} to change the plant's state in a manner the sensor 18 can accurately sense. Yet another example of a control limit is the finite time required of a processor to process the various input signals to the controller and to generate the controller's output signals.

Turning now to FIG. 3, the hedge unit 20 includes a hedge model 200 having a plant model 201 without the plant characteristic that is to be hedged and a plant model 202 with the plant characteristic(s) that is/are to be hedged, and a comparator 204. These elements of the hedge unit 20 can be implemented as one or more software modules or functions within the hedge unit 20. The plant model 201 without the characteristic(s) is coupled to receive the input control signal d_{in} , and the plant state signal x_p . The plant model 202 with the characteristic(s) generates a first signal that indicates the predicted plant response to the input control signal d_{in} given the plant state signal x_p . The plant model 202 with the plant characteristic(s) that is to be hedged is coupled to receive the command control signal d_{cmd} and the plant state signal x_p . Based on these signals, the plant model 202 with the characteristic(s) to be hedged is used to generate a second signal. The comparator 204 is coupled to receive the first signal from the plant model 201 not having the plant characteristic to be hedged, and the plant model 202 having the characteristic(s) to be hedged. The comparator 204 differences the first and second signals to generate the hedge signal v_h . The hedge signal v_h in effect isolates the plant and/or system characteristic(s) that are to be hedged.

In FIG. 4, details of a possible implementation of the reference model unit 22 are shown. The reference model unit 22 includes a reference model 220, a comparator 222, and a state computation unit 224. The reference model 220 receives the commanded state signal x_r , and the reference model state signal x_{rm} from the state computation unit 224. The reference model 220 generates a signal x_r' based on the commanded state signal x_r and the reference model state signal x_{rm} . The reference model 220 is a software module or function that maps the commanded state signal x_r to the reference model state signal x_{rm} . The reference model state signal x_{rm} represents the target plant state corresponding to the commanded state signal x_r . The signal x_r' from the reference model 220 is supplied to the comparator 222. The comparator 222 also receives the hedge signal v_h from the hedge unit 20. The comparator 222 subtracts the hedge signal v_h from the signal x_r' to generate the signal x_r'' . The signal x_r'' is supplied to the state computation unit 224. The state computation unit 224 computes the reference model state signal x_{rm} from the signal x_r'' . More specifically, the state computation unit 224 computes scalar, derivative and/or integral values of the signal x_r'' according to the form or order of the reference model. Accordingly, the state computation unit 224 generates the reference model state signal x_{rm} as a vector with scalar, integral and/or derivative terms using the commanded state signal x_r , as modified in the unit 22 by the hedge signal v_h , and the reference model 222. The state computation unit 224 supplies the resulting reference model state signal x_{rm} or predetermined terms thereof as a feedback signal to the reference model 220. The state computation unit 224 also supplies the reference model state signal x_{rm} to the comparator 24. The reference model state signal x_{rm} includes the reference model response to the

characteristic to be hedged so that it can be used in the comparator 24 to extract from the plant state signal x_p the contribution to plant state resulting from the presence of the characteristic(s). Accordingly, the effect of the characteristic is eliminated or at least reduced from the tracking error signal e so that the adaptation law unit 26 will not adapt to the characteristic's impact on the system 10 or the plant 12. Of course, it may not be possible to remove all impact of the characteristic from the tracking error signal e . However, enough of the impact of the characteristic should be removed from the tracking error signal e so that system control of the plant will not be compromised. Satisfaction of this objective depends upon pre-specifications for the system based on control performance objectives, control stability, and the nature of the control system 10 and plant 12.

FIG. 5 is a possible implementation of the system 10. The actuator 16, the sensor 18, the operator interface unit 28, the command unit 32, a processor 34, and a memory 36 are coupled to a bus 38. The processor 34 can be a microprocessor or a microcontroller, for example. For example, the processor 34 could be a microprocessor with 64-bit word size operating at a 1.0 GHz instruction execution cycle. The processor 34 can be a Pentium® III microprocessor commercially-available from Intel Corporation, Santa Clara, Calif., or an Athlon® microprocessor from Advanced Micro Devices®, Inc., Sunnyvale, Calif. The memory 36 stores a control program 360 and data 362. The control program 360 is executed by the processor 34 in the performance of a control cycle of the adaptive control system 10. The control program 360 includes the software modules used to implement the controller 14, the hedge unit 20, the reference model unit 22, the comparator 24, and the adaptation law unit 26. The data 362 includes data used by the processor 34 in executing the software modules of the control program 360 or temporary data generated by the processor 34 as it executes the control program 360. In the operation of the system 10 of FIG. 5, the sensor 18 has sensed the state of plant 12 to generate the plant state signal x_p . The plant state signal x_p has been stored as data 362 in the memory 36 via the bus 38. Also, signals required for use in the next control cycle which could include the adaptive control signal v_{ad} and the plant state signal x_p and possibly other signals as well, are stored as data 362 in the memory 36. Alternatively, the adaptive control signal v_{ad} can be generated in the control cycle under execution using a fixed-point solution. The command unit 32 writes the commanded state signal x_r for the current control cycle as data 362 stored in the memory 36. In executing its control program 360 over the control cycle under execution, the processor 34 reads the commanded state signal x_r from the memory 36. The processor 34 also reads the plant state signal x_p and the adaptive control signal v_{ad} and generates the input control signal d_{in} and the command control signal d_{cmd} . Alternatively, the plant state signal x_p or a construction thereof from the sensor signal derived from a time after execution of the previous control cycle can be stored in memory for use in the next control cycle. The processor 34 supplies the command control signal d_{cmd} to the actuator 16 that controls the state of the plant 12 based thereon. The processor 34 also executes the control program 360 to generate the hedge signal v_h based on the input control signal d_{in} , the command control signal d_{cmd} , the plant state signal x_p , and optionally also on the actuator state signal x_a . Processor 34 further executes the control program 360 to generate the reference model state signal x_{rm} . The processor 34 subtracts the reference model state signal x_{rm} from the plant state signal x_p to generate the tracking error signal e . The processor 34 uses the tracking

error signal e and optionally also the plant state signal x_p and a pseudo-command signal v_{pc} , to generate the adaptive control signal v_{ad} . The processor **34** can store any signals needed for the next control cycle in the memory **36**.

The method of FIG. 6 follows operation of the adaptive control system **10** of FIGS. 1–5 over a control cycle. In step S1 of FIG. 6, the method begins. In step S2 of FIG. 6, the command unit **32** generates the commanded state signal x_r based on the operator's action and/or operator-generated signal. In step S3 the controller generates the input control signal d_{in} based on the commanded state signal x_r , the plant state signal x_p from sensor **18** and the adaptive control signal v_{ad} generated by the adaptation law unit **26**. Alternatively, the commanded state signal x_r is first used by the reference model unit **22** to generate the reference model state signal x_{rm} . The controller **14** generates the input control signal d_{in} based on the reference model state signal x_{rm} , and the plant state signal x_p from the sensor **18**, and the adaptive control signal v_{ad} generated by the adaptation law unit **26**. In step S4 the controller **14** generates the control signal d_{cmd} based on the commanded state signal x_r , and the plant state signal x_p and adaptive control signal v_{ad} using the control allocation and characteristic unit **142** of the controller **14**. In optional step S5 the controller **14** generates a pseudo-control signal v_{pc} based on the commanded state signal x_r , and the plant state signal x_p and the reference model state signal x_{rm} . In step S6, the controller **14** supplies the control signal d_{cmd} the actuator **16** to control the plant **12**. In step S7 the sensor **18** senses the plant state. In step S9 the controller **14** generates the plant state signal x_p based on the sensed plant state. In step S10 the processor **34** receives the plant state signal x_p . In step S11 the hedge unit **20** generates the hedge signal v_h based on the input control signal d_{in} , the command control signal d_{cmd} , optionally on the actuator state signal x_{ad} , the plant model with the characteristic whose effect is to be removed from the tracking error signal e supplied to the adaptation law unit **26**, and the plant model without the characteristic whose effect is to be removed from the tracking error signal. In step S12 the reference model unit **22** generates the reference model state signal x_{rm} , based on the commanded state signal x_r , the hedge signal v_h , and the reference model. In step S13 the comparator **24** generates the tracking error signal e based on the plant state signal x_p and the reference model state signal x_{rm} . In step S14 the adaptive law unit generates the adaptive control signal v_{ad} based on the tracking error signal e and/or the pseudo-control signal v_{pc} generated by the controller **14**. In step S15, the processor **34** stores any signals required for the next control cycle in the memory **36**. Such signals might include the plant state signal x_p and the adaptive control signal v_{ad} . In step S16 the method of FIG. 6 ends.

FIGS. 7–13 are views of an exemplary embodiment of the adaptive control system **10**. In FIG. 7 the controller **14** comprises the control model **140** and the control allocation and characteristic unit **142**. The control model **140** includes a linear control module **144**, a summing unit **146**, and an approximate dynamic inversion module **148**. The linear control module **144** generates a linear control signal v_{lc} , based on the tracking error signal e . More specifically, the linear control module **144** applies a linear control law to map the tracking error signal e to the linear control signal v_{lc} . The reference model unit **22** generates the reference model signal v_{rm} that is a subset of the vector of the reference model state signal x_{rm} . The linear control module **144** and the reference model unit **22** are designed to control the plant **12** for target system response and stability using design techniques well-known to those of ordinary skill in the art. In the exemplary

embodiment of FIG. 7, the adaptation control unit **26** includes a neural network **260**. The neural network **260** receives as inputs the plant state signal x_p and a pseudo-control signal v_{pc} , and the tracking error signal e . The neural network **260** maps the plant state signal x_p to the adaptive control signal v_{ad} using connection weights adaptively set each control cycle by the tracking error signal e and the pseudo control signal v_{pc} . By updating the connection weights of the neural network **260** with successive control cycles, the system **10** is adaptive to changes over time in the plant **12** as well as the system **10**. The pseudo-control signal v_{pc} is used in part to adapt the connection weights of the neural network **260** generated in the control model **140**. In the control model **140**, the adaptive control signal v_{ad} is subtracted from the sum of the reference model signal v_{rm} and the linear control signal v_{lc} in the summing unit **146** to generate pseudo-control signal v_{pc} . The pseudo-control signal v_{pc} is supplied to the hedge unit **20** for optional use in generating the hedge signal v_h . The pseudo-control signal v_{pc} is also supplied to a dynamic inversion unit **148** of the control model **140**. The dynamic inversion unit **148** inverts the pseudocontrol signal v_{pc} based on an inversion function representing the plant control response. The inversion function is a function of the plant state signal x_p and the pseudo-control signal v_{pc} . The inversion function maps these signals to the input command signal d_{in} . The remainder of the adaptive control system **10** is similar in function and configuration to previously described embodiments.

FIG. 8 is an exemplary embodiment of the hedge unit **20** of FIG. 7. In this embodiment, the first signal d_1 supplied to the comparator **204** can be generated in one of two ways. More specifically, the plant state signal x_p and the input command signal d_{in} can be supplied to the plant model **210** that includes an inversion function to generate the first signal d_1 based on these signals. Alternatively, the pseudo-control signal v_{pc} can be supplied as the first signal d_1 directly to the comparator **204**. The command control signal d_{cmd} is supplied to the plant model **202** that includes an actuator model **206** for one or more characteristics of the actuator **16** to be hedged, and a plant model **208** with one or more characteristics of the plant **12** to be hedged. The command control signal d_{cmd} is fed to the actuator model **206** to generate command signal δ . The command signal δ is supplied to the plant model **208** along with the plant state signal x_p for use in generating the second signal d_2 supplied to the comparator **204**. The comparator **204** generates the hedge signal v_h by subtracting the first and second signals d_1 , d_2 to isolate the effect of the characteristics to be hedged.

In FIG. 9 a relatively detailed example of the reference model unit **22** is shown. The reference model unit **22** in this case is second-order, and has constant, derivative, and double derivative terms. The reference model unit **22** includes a comparator **222**, a multiplier **226**, a summing unit **228**, integrators **230**, **232**, and multipliers **234**, **236**. The multiplier **226** multiplies the commanded state signal x_r by a predetermined constant ω_n^2 to generate a modified signal supplied to the summing unit **228**. The summing unit **228** subtracts signals from the multipliers **234**, **236** from the modified signal from the multiplier **228** to generate the reference model signal v_{rm} . The summing unit **228** supplies the reference model signal v_{rm} to the controller **14**. The summing unit **228** also supplies the reference model signal v_{rm} to the comparator **222**. The comparator **222** subtracts the hedge signal v_h from the reference model signal v_{rm} to generate a signal supplied to the integrator **230**. The integrator **230** integrates the signal from comparator **222** to generate integrated signal \dot{x}_{rm} . The integrated signal \dot{x}_{rm} is

supplied to the integrator 232 to generate the reference model state signal x_{rm} that in this case has a “constant” term, a derivative term, and a second-derivative term. The reference model state signal x_{rm} is supplied to the comparator 24. The integrated signal \dot{x}_{rm} from the unit 230 is also supplied to the multiplier 234 that multiplies this integrated signal by the constant $2\zeta\omega_n$ in which ζ and ω_n are constants, and supplies the resulting signal to the summing unit 228. The “constant” term from the reference model state signal x_{rm} is also supplied to the multiplier 236 that multiplies this signal by the constant ω_n^2 to generate a signal supplied to the summing unit 228. The signals from multipliers 234, 236 are subtracted from the signal from multiplier 226 to generate the reference model signal v_{rm} .

FIG. 10 is a diagram of a neural network 260. The neural network 260 includes an input layer 262, a hidden layer 264, and an output layer 266. The input layer 262 has N_1 nodes receiving elements of the plant state signal \bar{x} and the pseudo-control signal v_{pc} , N_1 being a positive integer. The N_1 th nodes of the input layer 262 are multiplied by respective connection weights V to generate the input signals to the N_2 nodes of the hidden layer 264, N_2 being a positive integer. The weighted input signals to the hidden layer 264 are supplied as input signals to the sigmoidal activation function $\sigma(z)$ of the form:

$$\sigma(z) = \frac{1}{1 + e^{-az}} \quad (1)$$

in which a is a predetermined constant and z represents the V -weighted input signals from the input layer 262. The outputs from the hidden layer 264 are weighted by the connection weights W , and are supplied as input signals to respective nodes 1– N_3 of the output layer 266. These nodes add respective input signals to generate the adaptive control signal $-v_{ad}$. The mapping of the plant state signal x_p to the adaptive control signal v_{ad} performed by the neural network 260 can be expressed as:

$$v_{ad} = y_i = \sum_{j=1}^{N_2} \left[w_{ij} \sigma \left(\sum_{k=1}^{N_1} v_{jk} \bar{x}_k + b_{vj} \right) + b_{wi} \right] \quad i = 1, 2, \dots, N_3 \quad (2)$$

where N_1 , N_2 , N_3 are the number of nodes in the input, hidden, and output layers 262, 264, 266, respectively, referenced by corresponding indexes k , j , i . The connection weights v_{jk} and w_{ij} are set adaptively by the states of the tracking error signal e and the N_1 inputs to the neural network input layer 262. The constants b_{vj} and b_{wi} are predetermined. In matrix form equation (2) can be expressed as:

$$v_{ad} = y = W^T \sigma(V^T \bar{x}) \quad (3)$$

in which \bar{x} is the neural network input signal, V^T is the transpose of the connection weight vector V , σ is the sigmoidal activation function, W^T is the transpose of the connection weight vector W , and $y = v_{ad}$ is the adaptive control signal. The signal v_{ad} can either be multiplied by “-1” or mapped by the neural network 260 to generate the signal $-v_{ad}$ for supply to the controller 14.

The manner in which the tracking error signal e and the input layer signal are used to adapt the connection weights V and W is now described. The pseudo-control signal v_{pc} is generated using the reference model signal v_{rm} , the linear control signal v_{lc} , and the adaptive control signal v_{ad} , as follows:

$$v_{pc} = v_{rm} + v_{lc} - v_{ad} \quad (4)$$

The pseudo-control signal v_{pc} is related to the acceleration term of the reference model state. The pseudo-control signal can be further augmented by terms as may be required to support proof of boundedness. An example of a term is commonly referred to as the robustifying term and is well known to those of ordinary skill in the art. Dynamic inversion is used to reduce the control design problem to that of a control design for a linear, time-invariant plant. However, as is well-known to those of ordinary skill in this technology, use of an imperfect model in the dynamic inversion process can corrupt the desired relationship between acceleration of the plant state vector and the pseudo-control by an amount Δ often referred to as an inversion error. This relationship between acceleration of the plant state, pseudo-control, and the inversion error is defined in Equation (5).

$$\ddot{x}_p = v_{pc} + \Delta \quad (5)$$

The derivative of the tracking error signal e can be expressed as:

$$\dot{e} = Ae + b(\Delta + v_{ad}) \quad (6)$$

in which A is Hurwitz. The output of the neural network v_{ad} is used to approximate the inversion error, Δ so that the error dynamics of Equation (6) will remain bounded, and tracking error is minimized. The constant ζ is defined by the equation:

$$\zeta = e^T P b \quad (7)$$

in which e^T is the transpose of the tracking error signal e , b is a predetermined matrix constant from Equation (6), and P is the solution of a Lyapunov equation (8).

$$A^T P + P A = -Q \quad (8)$$

in which Q is a positive definite matrix. The adaptation law for updating the neural network weights and implemented by the adaptation law unit 26 can be expressed as:

$$\dot{V} = -[\bar{x} \zeta W^T \sigma' + \lambda_v \zeta |V|] \Gamma_v \quad (9)$$

$$\dot{W} = -\Gamma_w \frac{1}{W(\sigma - \sigma^T \bar{x})} \zeta + \lambda_w \zeta |W| \quad (10)$$

in which \dot{V} is the derivative of the connection weight vector V of the neural network 260, \dot{W} is the derivative of the W weight vector of the neural network 260, $\sigma'(z)$ is the partial derivative of sigmoidal function $\sigma(z)$ with respect to z , λ_v , λ_w , ζ , Γ_v , Γ_w are predetermined vectors, and x is the plant state signal.

For the case of a second-order reference model (FIGS. 7–10) the remaining characteristics are:

$$\ddot{x}_p = f(x_p, \dot{x}_p, d_{cmd}(d_{in})) \quad (11)$$

$$\ddot{x}_{rm} = v_{rm} - v_h = f_{rm}(x_{rm}, \dot{x}_{rm}, x_p) - v_h \quad (12)$$

$$v_{lc} = K_p(x_{rm} - x_p) + K_D(\dot{x}_{rm} - \dot{x}_p) \quad (13)$$

$$v_{pc} = v_{rm} + v_{lc} - v_{ad} \quad (14)$$

$$v_h = v_{pc} - \hat{f}(x_p, \dot{x}_p, d_{cmd}(d_{in})) \quad (15)$$

$$d_{in} = \hat{f}^{-1}(x_p, \dot{x}_p, v_{pc}) \quad (16)$$

in which K_p and K_d are predetermined constants. Equation (16) corresponds to the dynamic inversion unit 148 of FIG. 7. The tracking error signal e can be expressed as the vector of differences:

15

$$e = \begin{bmatrix} \dot{x}_{rm} - \dot{x}_p \\ x_{rm} - x_p \end{bmatrix} \quad (17)$$

It can be shown that whether $\delta = d_{in} = d_{cmd}$ or $\delta = d_{in} \neq d_{cmd}$, the following equation holds:

$$\dot{e} = Ae + b[\Delta(\dot{x}_p, \ddot{x}_p, d_{cmd}) + v_{ad}] \quad (18)$$

Hence, due to the hedge signal v_h generated by the hedge unit **20**, the adaptive control system **10** is bounded with respect to tracking error and neural network weights. The plant will track the desired response as close as is possible within the limits of d_{cmd} . Without the hedge unit **20**, it can be shown that the system **10** would not be stable for cases in which $d_{in} \neq d_{cmd}$.

In FIG. **11** a special case of the control allocation and characteristic unit **142** is shown. More specifically, the unit **142** includes an operator interface unit **144**, and operator **146**, and a command unit **148**. The operator interface unit **144** receives the input command signal d_{in} and the plant state signal x_p , and generates a signal or display based on these signals. The operator **146** can be a human operator, a computer, or other machine, for example. In the case of a human operator, the operator interface unit generates a display based on the input command signal d_{in} and the plant state signal x_p . The operator **146** uses the display from the operator interface unit **144** to control the command unit **148** to generate the command control signal d_{cmd} . The command control signal d_{cmd} is supplied to the actuator **16** to control the state of the plant. The configuration of the unit **142** in FIG. **11** is useful in numerous contexts. For example, in an aircraft, it may be desirable to have an auto-pilot whose control of the aircraft is limited. In situations in which it is not desirable for the auto-pilot to control the aircraft, such as take-off or landing in which emergency maneuvers are more likely to be required, the aircraft's flight control system can be implemented to switch the operator **146** into the control loop with units **144** and **148** as shown in FIG. **11**. In this configuration, control and response characteristic(s) generated by the operator are hedged by the hedge unit **20**. One barrier to implementation of adaptive control systems in contexts such as aircraft is the stringent testing and certification required of adaptive control systems. Certification is made difficult by the fact that it may be exceedingly difficult or impossible to subject the adaptive control system to all plant states it is likely to encounter. The configuration of FIG. **11** provides the advantage of permitting the use of an adaptive control system in which the pilot operator can control the aircraft without causing the control system to adapt to the pilot's control and response. Accordingly, the configuration of FIG. **11** should facilitate testing and certification of an adaptive control system incorporating the features of the unit **142** in FIG. **11**.

The adaptive control system **10** can be used in numerous applications. For example, the plant **12** can be a manned or unmanned vehicle. Such vehicle can be an aircraft, spacecraft, missile, or guided ordinance. In general, the adaptive control system **10** is assigned to control one degree of freedom of the plant **12**. The actuator **16**, the sensor **18**, the operator interface unit **28**, the operator **30**, and the command unit **32** depend upon the nature of the plant **12** and the degree of freedom thereof to be controlled by the adaptive control system **10**. For example, if the plant **12** is a guided vehicle such as an aircraft, spacecraft, missile or other guided ordinance, the actuator **16** could be a motor, a motor-driven screw, a hydraulic cylinder or other device

16

attached to a control surface such as an aileron, rudder, or stabilizer. Alternatively, the actuator **16** could be a pump or valve that generates air jet(s) to change the flow of air over the guided vehicle's surface, or a frame actuator that changes the shape of the guided vehicle's surface. In addition, the actuator **16** could be thrust controllers to control the direction of thrust generated by a power plant of the aircraft. Such actuators can be used to control the degree of freedom (e.g., pitch, roll, or yaw) that is controlled by the adaptive control system **10**. In the guided vehicle context, the sensor **18** can be a gyroscope or other device to measure the degree of freedom controlled by the actuator **16**. In the case of a manned vehicle, the operator **30** can be a human, the operator interface unit **28** a display, and the command unit **32** a control stick and/or flight control system, for example. If the plant **12** is an automobile, the actuator **16** can be a valve for a fuel injection port, a hydraulic cylinder to move a braking element into contact with a brake drum, a transmission or other element. In this case, the sensor **18** can be a speedometer, a pressure sensor in an engine cylinder, an inertial sensor, or other elements. The plant **12** could also be a satellite, and the actuator **16** could be a thruster to orient and position the satellite in orbit. The satellite's actuator **16** could be a motor-driven electromechanical device to position a solar panel or transceiver unit in a desired direction. In the satellite context, the sensor **18** could be a gyroscope, for example. As another example, the operator **30** can be a combination of an auto-pilot and a human operator to take control of the plant in circumstances in which the auto-pilot is not to control the plant. Such implementation can be used in aircraft, for example. The command unit **32** can be programmed to switch control between a machine and human operator to control the aircraft plant **12**. The hedge unit **20** can generate the hedge signal to hedge characteristics of the human control of the command unit **32** for stable control of the aircraft plant. It should be understood that the use of a vehicle context in the foregoing description is exemplary only, and is not intended to limit the scope or context in which the invented adaptive control system **10** can be used. Those of ordinary skill in the art should understand that the system **10** can be used in numerous other contexts and environments, such as manufacturing plants, power generation stations, and numerous other types of plants.

Any trademarks listed herein are the property of their respective owners, and reference herein to such trademarks is intended only to indicate the source of a particular product or service.

The many features and advantages of the present invention are apparent from the detailed specification and it is intended by the appended claims to cover all such features and advantages of the described methods and apparatus which follow in the true scope and spirit of the invention. Further, since numerous modifications and changes will readily occur to those of ordinary skill in the art, it is not desired to limit the invention to the exact implementation and operation illustrated and described. Accordingly, all suitable modifications and equivalents may be resorted to as falling within the scope and spirit of the invention.

What is claimed is:

1. A method executed by an adaptive control system, the method comprising the steps of:
 - a) generating an input control signal based on at least one of a reference model state signal, a commanded state signal, a plant state signal, and an adaptive control signal;
 - b) generating a command control signal based on at least one of a commanded state signal, a plant state signal, an

- adaptive control signal, and further based on control allocation and a control characteristic of a controller used to generate the command control signal;
- c) supplying the command control signal to an actuator;
 - d) controlling a state of the plant based on the command control signal;
 - e) sensing a state of the plant;
 - f) generating a plant state signal based on the sensing of the step (e);
 - g) generating a first signal based on the input control signal, the plant state signal, and a plant model without a plant characteristic for which the adaptive control system is not to adapt;
 - h) generating a second signal based on the command control signal, the plant state signal, and a plant model with the plant characteristic for which the adaptive control system is to adapt;
 - i) generating a hedge signal by differencing the first and second signals;
 - j) generating a reference model state signal by modifying the commanded state signal with the hedge signal to include the effect of the control allocation and control characteristic on plant state from the reference model state signal;
 - k) comparing the plant state signal and the reference model state signal;
 - l) generating a tracking error signal based on the comparing of the step (k); and
 - m) generating the adaptive control signal based on the tracking error signal.
2. A method as claimed in claim 1 further comprising the step of:
- n) generating the reference model signal based on the commanded state signal, the hedge signal, and a reference model representing the target response of the plant, the reference model signal used in the step (a) to generate the input control signal.
3. A method as claimed in claim 1 further comprising the step of:
- n) generating the reference model signal based on the commanded state signal, the hedge signal, and a reference model representing the target response of the plant, the reference model signal used in the step (b) to generate the command control signal.
4. A method as claimed in claim 1 further comprising the step of:
- n) generating a linear control signal based on the tracking error signal;
 - o) generating a reference model signal based on the commanded state signal, the hedge signal, and a reference model; and
 - p) generating a pseudo-control signal based on the linear control signal, the reference model signal, and the adaptive control signal, the pseudo-control signal used in the generation of the adaptive control signal in the step (m).
5. A method as claimed in claim 1 further comprising the step of:
- n) generating the commanded state signal based on a control action from an operator.
6. A method as claimed in claim 1 further comprising the step of:
- n) generating the commanded state signal based on a signal generated by an operator that is a computer.

7. A method as claimed in claim 1 further comprising the step of
- n) generating a display for an operator based on the input control signal, the operator generating the command control signal based on the display.
8. A method as claimed in claim 1 wherein the plant is an aircraft and/or spacecraft.
9. A method as claimed in claim 1 wherein the plant is an automobile.
10. A method as claimed in claim 1 wherein the plant is an unmanned vehicle.
11. A method as claimed in claim 4 wherein the adaptive control signal is generated in the step (m) based on the plant state signal, the step (m) performed by a neural network having connection weights adjusted based on the tracking error signal and the pseudo-control signal, the neural network mapping the plant state signal to the adaptive control signal in the performance of the step (m).
12. A method as claimed in claim 4 wherein the plant state signal is used in the step (m) to generate the adaptive control signal.
13. A method as claimed in claim 5 wherein the operator is human, the method further comprising the step of:
- o) generating a display based on the plant state signal, the display used by the operator to generate the commanded state signal in the step (n).
14. An adaptive control system coupled to receive a command state signal indicative of a target state of a plant controlled by the adaptive control system, the adaptive control system comprising:
- a controller coupled to receive the commanded state signal, a plant state signal, and an adaptive control signal, the controller generating an input command signal based on the commanded state signal, the plant state signal, the adaptive control signal, and a control model, and the controller generating a command control signal based on the commanded state signal, the plant state signal, the adaptive control signal, the control model, control allocation of the controller, and at least one control characteristic of the controller, the controller coupled to supply the command control signal to the plant to control the plant's state;
 - an actuator coupled to receive the command control signal, and affecting physical control of the plant's state based on the command control signal;
 - a sensor coupled to sense the plant state, and generating a plant state signal based on the sensed plant state;
 - a hedge unit coupled to receive the input control signal, the command control signal, and the plant state signal, and generating a hedge signal to modify the command state signal based on the input control signal, the command control signal, the plant state signal, and a hedge model indicative of a characteristic of at least one of the plant and the adaptive control system, to remove the effect of the characteristic on a tracking error signal;
 - a reference model unit coupled to receive the command state signal and the hedge signal, the reference model unit generating a reference model state signal based on the commanded state signal and a hedge signal;
 - a comparator unit coupled to receive the reference model state signal and the plant state signal, and generating a tracking error signal based on a difference between the plant state signal and the reference model state signal; and
 - an adaptation law unit coupled to receive the tracking error signal, and generating the adaptive control signal

19

based on the tracking error signal, the adaptation law unit coupled to supply the adaptive control signal to the controller.

15 **15.** An adaptive control system as claimed in claim 14 wherein the controller generates the input control signal and the command control signal further based on the reference model state signal.

16. An adaptive control system as claimed in claim 14 wherein the characteristic is a time delay between generation of the commanded state signal by the controller at a time; and receipt by the controller of the plant state signal resulting from the commanded state signal generated at the time.

17. An adaptive control system as claimed in claim 14 wherein the characteristic is a time delay between generation of a state by the plant in response to the command control signal, and sensing of the state of the plant resulting from the command control signal.

18. An adaptive control system as claimed in claim 14 wherein the characteristic pertains to a control limit of the actuator used to control the plant.

19. An adaptive control system as claimed in claim 14 wherein the commanded state signal is generated by an operator, the adaptive control system further comprising:

an operator interface unit coupled to receive the plant state signal, the operator interface unit relaying the plant state to the operator; and

a command unit operable by the operator, and generating the command state signal based on the operator's control action.

20. An adaptive control system as claimed in claim 14 wherein the operator interface is a display generated based on the plant state signal, and the operator is a human being that generates the control action to the command unit to generate the commanded state signal.

21. An adaptive control system as claimed in claim 14 wherein the commanded state signal is generated by a machine operator based on the plant state signal.

20

22. An adaptive control system as claimed in claim 14 wherein the adaptation law unit comprises a neural network having connection weights determined by the tracking error signal, the neural network mapping the plant state signal to the adaptive control signal based on the connection weights to generate the adaptive control signal.

23. An adaptive control system as claimed in claim 14 wherein the controller includes a dynamic inversion unit to generate the command control signal.

24. An adaptive control system as claimed in claim 14 wherein the input control signal is used to generate a display, and the operator generates a command control signal based on the display.

25. An adaptive control system as claimed in claim 14 wherein the plant is an aircraft and/or spacecraft.

26. An adaptive control system as claimed in claim 14 wherein the plant is an automobile.

27. An adaptive control system as claimed in claim 14 wherein the plant is an unmanned vehicle positioned remotely from the operator.

28. An adaptive control system as claimed in claim 18 wherein the control limit pertains to actuator end points.

29. An adaptive control system as claimed in claim 18 wherein the control limit pertains to actuator dynamics.

30. An adaptive control system as claimed in claim 18 wherein the control limit pertains to a rate limit of the actuator.

31. An adaptive control system as claimed in claim 18 wherein the control limit pertains to quantization effects of the actuator.

32. An adaptive control system as claimed in claim 22 wherein the controller generates a pseudo-control signal based on the commanded state signal and the plant state signal, the controller coupled to supply the pseudo-control signal to the neural network to adjust the connection weights of the neural network.

* * * * *