

**NASA  
Technical  
Memorandum**

NASA TM - 82584

**AN INVESTIGATION INTO THE PROBABILISTIC  
COMBINATION OF QUASI-STATIC AND  
RANDOM ACCELERATIONS**

By Richard W. Schock and Lenox P. Tuell

Systems Dynamics Laboratory  
Science and Engineering

May 1984



National Aeronautics and  
Space Administration

George C. Marshall Space Flight Center

1. REPORT NO. NASA TM -82584		2. GOVERNMENT ACCESSION NO.		3. RECIPIENT'S CATALOG NO.	
4. TITLE AND SUBTITLE An Investigation Into the Probabilistic Combination of Quasi-Static and Random Accelerations				5. REPORT DATE May 1984	
				6. PERFORMING ORGANIZATION CODE ED24	
7. AUTHOR(S) Richard W. Schock and Lenox P. Tuell				8. PERFORMING ORGANIZATION REPORT #	
9. PERFORMING ORGANIZATION NAME AND ADDRESS George C. Marshall Space Flight Center Marshall Space Flight Center, Alabama 35812				10. WORK UNIT NO.	
				11. CONTRACT OR GRANT NO.	
12. SPONSORING AGENCY NAME AND ADDRESS National Aeronautics and Space Administration Washington, D.C. 20546				13. TYPE OF REPORT & PERIOD COVERED Technical Memorandum	
				14. SPONSORING AGENCY CODE	
15. SUPPLEMENTARY NOTES Prepared by Environmental Analysis Branch, Systems Dynamics Laboratory, Science and Engineering.					
16. ABSTRACT  The development of design load factors for aerospace and aircraft components and experiment support structures, which are subject to a simultaneous vehicle dynamic vibration (quasi-static) and acoustically generated random vibration, require the selection of a combination methodology. Typically, the procedure is to define the quasi-static and the random generated response separately, and arithmetically add or root sum square to get combined accelerations. Since the combination of a probabilistic and a deterministic function yield a probabilistic function, a viable alternate approach would be to determine the characteristics of the combined acceleration probability density function and select an appropriate percentile level for the combined acceleration. The following paper develops this mechanism and provides graphical data to select combined accelerations for most popular percentile levels.					
17. KEY WORDS Stochastic loads, dynamics, vibro-acoustics, load combination methodology			18. DISTRIBUTION STATEMENT  Unclassified - Unlimited		
19. SECURITY CLASSIF. (of this report) Unclassified		20. SECURITY CLASSIF. (of this page) Unclassified		21. NO. OF PAGES 14	
				22. PRICE NTIS	

## TABLE OF CONTENTS

	Page
INTRODUCTION .....	1
DISCUSSION .....	1
REFERENCES .....	9

## LIST OF ILLUSTRATIONS

Figure	Title	Page
1.	Single degree-of-freedom component idealization .....	3
2.	Time history combined quasi-static and random response .....	4
3.	Combined sinusoidal/random distributions VRS random only .....	4
4.	Random signal .....	5
5.	PDF of random signal .....	5
6.	Sinusoidal signal .....	6
7.	PDF of sinusoidal signal .....	6
8.	Combined sinusoidal/random signal .....	7
9.	PDF of combined signal .....	7
10.	CDF of combined signal .....	8
11.	Combined acceleration g level for selected values of the CDF .....	8

## TECHNICAL MEMORANDUM

### AN INVESTIGATION INTO THE PROBABILISTIC COMBINATION OF QUASI-STATIC AND RANDOM ACCELERATIONS

#### INTRODUCTION

The development of design load factors for aerospace and aircraft components and experiment support structures, which are subject to simultaneous vehicle dynamic vibration (quasi-static) and acoustically generated random vibration, require the selection of a combination methodology. Typically, the vehicle dynamic vibration is low frequency, transient, and deterministic. The random response is typically narrow band random whose characteristics are described probabilistically with a normal distribution of instantaneous values and a Rayleigh peak distribution. The combination of quasi-static and random response of the single degree-of-freedom system shown in Figure 1 is illustrated in Figure 2.

Since component support structure design limits generally are defined during the simultaneous occurrence of the two loads, the combination methodology is important from weight and qualification status.

The current practice to obtain the combined g level  $g_t$  is generally similar to the following.

- 1) Calculate the quasi-static (QS) maximum response.
- 2) Calculate the Grms response to random input by Miles relationship and multiply by a factor to get peak. If a factor of 3 is used, this is the same as the 99.87 percentile level of the instantaneous distribution.
- 3) Add them on a directional basis to get combined  $g_t$ .

The percentile level for the combined acceleration developed this way is not calculable. It would seem, however, that a viable alternate approach would be to determine the characteristics of the probability density function of the combined acceleration (QS and random) and select an appropriate percentile level for a combined  $g_t$ . The following discussion develops that scenario.

#### DISCUSSION

If the time history combined functions of Figure 2 can be idealized as  $y(t) = A \sin \omega t + r(t)$ , where the randomly varying function  $r(t)$  is normally distributed about a zero mean with variance  $\sigma_r^2$  and has a normal probability density function (PDF) of:

$$f(r) = \frac{1}{\sigma_r \sqrt{2\pi}} \exp \left( -r^2 / 2\sigma_r^2 \right) \quad (1)$$

Then the PDF of the random function superimposed on the sinusoid is [1,2,3,4]:

$$p(y) = \frac{1}{\pi \sigma_r \sqrt{2\pi}} \int_{-\pi/2}^{\pi/2} \exp \left\{ -\frac{1}{2} \left( \frac{y - A \sin \theta}{\sigma_r} \right)^2 \right\} d\theta \quad (2)$$

where  $\sigma_r$  is the standard deviation of the random distribution and A is the peak amplitude of the sinusoid.

Figure 3 illustrates the characteristics of equations (1) and (2). Figure 3A shows a comparison between the combined PDF and the normal distribution  $f(r)$  for a random distribution with a variance  $\sigma_r^2$  equal to 0.09 of the sinusoidal variance  $\sigma_s^2$ . Obviously, as the random variance approaches 0, the combined distribution approaches a sinusoidal distribution.

Figure 3B shows a comparison between the combined distribution  $p(y)$  and the normal distribution  $f(r)$  for a superimposed random distribution with a variance  $\sigma_r^2$  equal to the sinusoidal variance  $\sigma_s^2$ . Obviously, as the random variance gets very large in comparison with the sinusoidal variance, the combined PDF approaches the random PDF.

Figures 4 through 10 illustrate the combining of a banded random white noise with a sinusoidal signal. The 100 to 600 Hz band random is illustrated in Figure 4. Its instantaneous distribution is shown in Figure 5. The sine wave and its distribution are shown in Figures 6 and 7, respectively. The RMS of the sine is equal to approximately three times the RMS of the random. The combined signal, its instantaneous distribution, and cumulative probability are shown in Figures 8, 9, and 10 respectively.

For a random distribution superimposed on a sine wave, the variance of the combined distribution is:

$$\begin{aligned} \sigma_c^2 &= \sigma_s^2 + \sigma_r^2 \\ &= A^2/2 + \sigma_r^2 \end{aligned} \quad (3)$$

or, the standard deviation of the combined signal equals the root sum square (RSS) of the sinusoidal RMS and the random RMS values.

$$\sigma_c = \sqrt{\frac{A^2}{2} + (\sigma_{rms})^2} \quad (4)$$

With the variance of the combined signal and the PDF defined, one can obtain the combined  $g_c$  acceleration level appropriate for any selected cumulative probability level.

The use of this methodology is shown in Figure 11, for the pre-selected popular percentile values. The following scenario applies.

- 1) Determine maximum quasi-static response acceleration  $A$  in  $g$ 's.
- 2) Determine the  $g_{rms}$  response of the article to the random input.
- 3) Select the combined instantaneous probability level desired (0.95 to 0.99865).
- 4) Determine the ratio of peak quasi-static  $A$  to random  $g_{rms} \sigma_r$ .
- 5) From the appropriate curve, read the ordinate corresponding to  $A/\sigma_r$  and multiply by  $\sigma_r$  to get the quantile pertinent to the combination.

This process will give a combined acceleration ( $g$ s) value for the selected no-exceedance probability.

In summary, the PDF of a combined sine/random signal has been determined. This along with the known peak quasi-static and random response  $g_{rms}$  allows one to describe the combined signal in probabilistic terms. One then can describe  $g_c$  to any probability level desired. A rational selection of a combined quasi-static/random response acceleration can now be selected for any prescribed probabilistic percentile level.




Figure 1. Single degree-of-freedom component idealization.




Figure 2. Time history combined quasi-static and random response.




Figure 3. Combined sinusoidal/random distributions VRS random only.




Figure 4. Random signal.




Figure 5. PDF of random signal.






Figure 6. Sinusoidal signal.




Figure 7. PDF of sinusoidal signal.




Figure 8. Combined sinusoidal/random signal.




Figure 9. PDF of combined signal.




Figure 10. CDF of combined signal.




Figure 11. Combined acceleration g level for selected values of the CDF.

## REFERENCES

1. Rice, S. O.: Bell Systems Technical Journal, Vol. 24, January 1945.
2. Bennett, W. R.: Acoustical Society of America Journal, Vol. 15, January 1944.
3. Bennett, W. R.: Bell Systems Technical Journal, Vol. 23, January 1944.
4. Tuell, L. P.: Unpublished work, NASA, Marshall Space Flight Center, Alabama, 1982.

## APPROVAL

### AN INVESTIGATION INTO THE PROBABILISTIC COMBINATION OF QUASI-STATIC AND RANDOM ACCELERATIONS

By Richard W. Schock/Lenox P. Tuell

The information in this report has been reviewed for technical content. Review of any information concerning Department of Defense or nuclear energy activities or programs has been made by the MSFC Security Classification Officer. This report, in its entirety, has been determined to be unclassified.



G. F. McDONOUGH  
Director, Systems Dynamics Laboratory

## DISTRIBUTION

### INTERNAL

ED11  
H. Scofield

ED21  
R. Ryan

ED24  
R. Schock  
L. Tuell

ED31  
W. Dahm

ED41  
W. W. Vaughan

ER01  
J. Dozier

EH23  
W. McPherson

EP46  
N. Schlemmer

EP42  
C. Bianca  
V. Richard

CC01  
Mr. Wofford

AT01  
Mr. Akbay

AS24L  
MSFC Library (8 copies)

### EXTERNAL

NASA Scientific and Technical Information  
Facility (25 copies)  
P.O. Box 8757  
Baltimore/Washington International Airport  
Baltimore, MD 21240

Jet Propulsion Laboratory  
Attn: Charles Lifer  
John Barba, 157/316  
Dennis L. Kern, 144/218  
Dr. Ben K. Wada  
4800 Oak Grove Drive  
Pasadena, CA 91109

AFOSR/NA  
Attn: Dr. Anthony K. Amos  
Bldg. 410  
Bolling Air Force Base, DC 20332