


# NASA TECH BRIEF

## Marshall Space Flight Center



NASA Tech Briefs announce new technology derived from the U.S. space program. They are issued to encourage commercial application. Tech Briefs are available on a subscription basis from the National Technical Information Service, Springfield, Virginia 22151. Requests for individual copies or questions relating to the Tech Brief program may be directed to the Technology Utilization Office, NASA, Code KT, Washington, D.C. 20546.

### Time-Based Priority Selection for Analog Circuits



N-Channel Selection Circuit

(continued overleaf)

**The problem:**

Priority encoding has been available in digital circuits, but only on a binary basis. Thus, all channels must be recorded to determine the highest priority pulse or signal.

**The solution:**

An "unlimited channel capacity" multiplexing circuit is hierarchically structured to achieve time-based priority selection for analog signals.

**How it's done:**

The circuit is shown in the accompanying diagram. A preset analog threshold is detected by the comparator, which changes the state of flip-flop A. Flip-flop A delivers an output for channel encoding and, at the same time, triggers a monostable multivibrator. This pulse changes the state of flip-flop B, which allows the analog gate to conduct to the analog bus. The change in flip-flop B disables all other channels through their inputs to the common lock-out line. When an external reset occurs, all channels return to an available state. Diodes permit the outputs to be connected in a "wired-or" mode.

The illustration shows how the circuit may be expanded. The circuit could be used for any analog multiplexing system that requires time priority detection. These include, for example, automatic patient monitor-

ing systems and diagnostic test systems in the automotive and communications industry.

**Notes:**

1. This system is being considered for use with digital to analog converters.
2. No additional documentation is available. Specific questions, however, may be directed to:  
Technology Utilization Officer  
Marshall Space Flight Center  
Code A&PS-TU  
Marshall Space Flight Center, Alabama 35812  
Reference: B73-10154

**Patent status:**

Inquiries concerning rights for the commercial use of this invention should be addressed to:

Patent Counsel  
Marshall Space Flight Center  
Code A&PS-PAT  
Marshall Space Flight Center, Alabama 35812

Source: J. D. Fageol of  
Rockwell International Corp.  
under contract to  
Marshall Space Flight Center  
(MFS-24242)