


NASA TECH BRIEF



NASA Tech Briefs are issued by the Technology Utilization Division to summarize specific technical innovations derived from the space program. Copies are available to the public from the Clearinghouse for Federal Scientific and Technical Information, Springfield, Virginia, 22151.

Simple BCD Circuit Accurately Counts to 24



The problem: BCD (binary-coded-decimal) divide-by-24 counters are frequently used in digital control clocks to register hours and give a daily output signal. Such counters have been unnecessarily complicated and in some cases produce false output spikes in the transition to the 24th count.

The solution: A ripple-through counter using commercially available digital modules that incorporate *and* gates with flip-flops (bistable multivibrators). The counter requires only 6 modules and generates the transition from 23 to 00 (the 24th count) by means of feedback loops.

How it's done: Flip-flops 1, 2, 4, and 8 provide a BCD count to nine in the normal manner. The transition of flip-flop 8 from the "one" state to the "zero" state generates the carry to the following stage. When the 8th pulse is registered, normally closed gate C is opened and normally open gate A is closed. The 10th pulse, therefore, resets flip-flop 8 but does not set flip-flop 2 as it normally would. The resetting of flip-flop

8 causes flip-flop 10 to be set. The same process occurs when the 20th pulse is encountered, except that flip-flop 10 is reset and flip-flop 20 is set. At the same time, normally open gate B is closed and normally closed gate D is opened. When the 24th pulse arrives, it resets flip-flop 20 but cannot set flip-flop 4. The 24th pulse, therefore, resets the entire counter and produces the divide-by-24 output pulse.

Note: Inquiries concerning this invention may be directed to:

Technology Utilization Officer
 Goddard Space Flight Center
 Greenbelt, Maryland 20771
 Reference: B65-10225

Patent status: NASA encourages the immediate commercial use of this invention. Inquiries about obtaining rights for its commercial use may be made to NASA, Code AGP, Washington, D.C., 20546.

Source: M. L. Spafford
 (GSFC-317)

Category No. 01