


# NASA TECH BRIEF



NASA Tech Briefs are issued to summarize specific innovations derived from the U.S. space program, to encourage their commercial application. Copies are available to the public at 15 cents each from the Clearinghouse for Federal Scientific and Technical Information, Springfield, Virginia 22151.

## Current-Limiting Voltage Regulator



A voltage regulator has been designed to operate within preset current limits. The regulator acts as a circuit breaker to prevent overload failure and automatically resets when the overload is removed.

Normal voltage control is accomplished by the voltage sampling circuit consisting of  $Q_4$  and associated components,  $R_4$ ,  $R_6$ ,  $C_2$ ,  $R_7$ ,  $R_5$ , and zener diode  $D_1$ . An increase in the output voltage ( $E_0$ ) causes an increase in the current through  $Q_2$  with subsequent starving of the base of  $Q_1$ . This results in an output voltage drop ( $E_0$ ) to the level set by  $R_4$ .

Transistor  $Q_3$  is the current-limiting control device. Current sampling resistor  $R_{12}$  controls the current available through  $D_4$  to the base of  $Q_3$ . Zener diode  $D_4$  is forward biased as a conventional diode except

under very light load conditions.  $Q_3$  exercises some control as an output voltage regulating element under normal operating conditions to supplement the action of  $Q_4$ . Current limiting level is adjusted by the choice of  $R_9$ . The combination of  $R_9$  and  $R_3$  sets the operating level at the emitter of  $Q_3$  below current-limiting levels. Above the current-limiting level, the combination of  $R_9$ ,  $R_{10}$ , and  $R_3$  sets the voltage at the emitter of  $Q_3$  so that, as  $Q_1$  is shut off, excess power is dissipated in the parallel circuits of  $R_1$ ,  $R_2$ ,  $Q_2$ , and  $R_{10}$ ,  $CR_3$  and  $R_3$ .

The combination of  $R_8$  and  $D_3$  and the elements  $CR_2$ ,  $R_{11}$ , and  $D_4$  serve to provide temperature compensation. The remaining components are typical of series-type regulator circuits and do not deserve special mention.

(continued overleaf)

**Notes:**

1. The important feature of this circuit is the power dissipated in the series transistor  $Q_1$ , which is approximately constant from normal load to short-circuit condition. In the conventional current-limiting approach, the power dissipation of  $Q_1$  increases from normal load to short-circuit condition.
2. Details may be obtained from:

Technology Utilization Officer  
Manned Spacecraft Center  
Houston, Texas 77058  
Reference: B68-10305

**Patent status:**

This invention is owned by NASA, and a patent application has been filed. Royalty-free, nonexclusive licenses for its commercial use will be granted by NASA. Inquiries concerning license rights should be made to NASA, Code GP, Washington, D.C. 20546.

Source: E. F. Cleveland  
(MSC-11824)