



NASA NEN DVB-S2 Demonstration Testing for Enhancing Higher Data Rates for CubeSat/Small Satellite Missions at X-band and Ka-band August, 2020

Transforming space communications from the ground up.

			_ '
	S	A	
No.	No.X		١
			_
		1	

	<u>AUTHORS</u>	
Organization	Name	Contribution
	Yen Wong	Primary Author
	Scott Schaire	Presenter/
Goddard Space Flight		Contributor
Center	Steve Bundick	Contributors
	Peter Fetterer	
Booz Allen &	Trish Perrotto	Contributors
Hamilton	Peter Celeste	



Exploration & SPACE Communications



Near Earth Network (NEN) Overview



NASA NEN (Direct to Earth Coverage up to one million miles from Earth)







NEN DVB-S2 Demonstration Test for Enhancing Higher Data Rates at X/Ka-band



- ➤ A DVB-S2 high data rate demonstration test is planned to be conducted at the Wallops Flight Facility in 2020 for CubeSat/SmallSat missions for enhancing data rate performance
- ➤ The primary objective was to determine the BER performance and maximum achievable data rate for DVB-S2 over the NEN X-band 375 MHz and Ka-band 1.5 GHz channels
- DVB-S2 uses power and bandwidth efficient modulation and coding techniques to deliver performance approaching Radio Frequency (RF) channel theoretical limits
- ➤ The demonstration test will be conducted using a Cortex high rate receiver (HRD) with a Zodiac DVB-S2 demonstration license
- ➤ The NEN will develop BER curves for selected DVB-S2 modulation and coding schemes and data rates of interest, as well as summarize implementation loss performance for all test cases







Predicted DVB-S2 High Data Rate X-band Performance



- Analysis was performed to predict the maximum achievable data rates, based on DVB-S2 spectral efficiency and performance requirements as well as NEN station Cortex HDR capability
- ➤ The maximum channel symbol rate is 300 Msps with the roll-off factor of 0.25 for NEN X-band 375 MHz bandwidth
- The predicted maximum data rate = spectral efficiency x 300 Msps
- The prediction is for intermediate frequency (IF) loop back, pilots off, and additive white Gaussian noise (AWGN)

Mod/ Coding Rate	1/4	1/3	2/5	1/2	3/5	2/3	3/4	4/5	5/6	8/9	9/10
QPSK	147	170	236.7	296.6	356.5	396.6	446.2	476.16	496.4	530	536.4
8 PSK	1				534	594	668.4	N/A	743.4	793.8	803.7
16 PSK			1	The same of the sa	1	791	890	950	990	1057	1070
32 PSK							1111	1185.5	1235.7	1319	1336



Predicted DVB-S2 Ka-band Performance



- ➤ In the NEN Ka-band 1.5 GHz channel, the predicted maximum channel data rate equals the spectral efficiency times the channel symbol rate
- ➤ With the 1.5 GHz channel bandwidth, the channel symbol rate is the same as the station HDR receiver maximum symbol rate, which is 500 Msps

Mod/	1/4	1/3	≥2/5 <	1/2	3/5	2/3	3/4	4/5	5/6	8/9	9/10
Coding Rate			7/								
QPSK	245	328	394.7	494.4	594.5	661	743.7	793.5	827.3	883.3	894.3
8 PSK					890	990	1114	N/A	1239	1323	1340
16 PSK	\ A]					1318.5	1483	1582.8	1650	1761.5	1783.5
32 PSK							1850	1975.8	2059.5	2219	2226



Link Analysis for X-band



- ➤ A link analysis study was performed to determine X-band DVB-S2 Achievable Data Rate vs. MODCODEs and S/C Antenna Size
- Assumption:

S/C at LEO 625 km altitude, f = 8250 MHz, PA=2W, WG1 11.3 m G/T = 34.5 dB/K (clear sky), 3 dB implement loss, 3 dB link margin

	Mod/Coding	1/4	1/3	2/5	1/2	3/5	2/3	3/4	4/5	5/6	8/9	9/10
1	Rate	7/1	7/		7							
	QPSK	147	170	236.7	296.6	356.5	396.6	446.2	476.16	496.4	530	536.4
	Antenna Gain, dBi	5.68	6.15	7.73	9.03	10.26	11.13	12.07	12.72	13.03	14.23	14.45
	8 PSK		مسمأ	,	4	534	594	668.4	N/A	743.4	793.8	803.7
	Antenna Gain, dBi				5	13.35	14.65	15.94	N/A	17.37	18.72	19.01
	16 APSK				LA /		791	890	950	990	1057	1070
	Antenna Gain, dBi				A		17.73	18.24	19.07	19.64	20.92	21.16
	32 APSK		The state of the s	The same of the sa			/	1111	1185.5	1235.7	1319	1336
	Antenna Gain, dBi							20.78	21.74	22.31	23.72	24.08



Link Analysis for Ka-band



> Assumption:

S/C at 625 km altitude, f = 26000 MHz, S/C PA = 5 W, Alaska Station 11m, G/T= 40.6 dB/K (clear sky), 3 dB implementation loss, 3 dB link margin.


Mod/Coding Rate	1/4	1/3	2/5	1/2	3/5	2/3	3/4	4/5	5/6	8/9	9/10
QPSK	245	328	394.7	494.4	594.5	661	743.7	793.5	827.3	883.2	894.3
Antenna Gain, dBi	//11.92	13.03	13.97	15.27	16.50	17.37	18.30	18.96	19.45	20.47	20.69
8 PSK				1 4	890	990	1114	N/A	1239	1323	1340
Antenna Gain, dBi	У				19.79	20.93	22.18	N/A	23.62	24.96	25.25
16 APSK			L	> T		1318.5	1483	1582.8	1650	1761.5	1783.5
Antenna Gain, dBi						23.24	24.48	25.31	25.87	27.16	27.40
32 APSK			-	1			1850	1975.8	2059.5	2199	2226
Antenna Gain, dBi							27.01	27.98	29.55	29.96	30.31



Conclusion




- ➤ A DVB-S2 high data rate demonstration test is planned to be conducted at the Wallops Flight Facility in 2020 for CubeSat/SmallSat missions for enhancing data rate performance
- ➤ The maximum data rate is predicted to achieve 1.3 Gbps at X-band 375 MH and 2.2 Gbps at Ka-band 1.5 GHz channels with today's station receiver capability
- ➤ A future station receiver upgrade will enable the achievable data rate to above 5 Gbps (10 Gbps with dual polarization) at Ka-band
- ➤ DVB-S2 will increase science data return for all missions and enable support for a greater number of CubeSats/SmallSats at high data rates
- ➤ The NEN is actively seeking additional flight and ground solutions for evaluation and welcomes contact for technical discussions





X-band Achievable Data Rates vs. Spacecraft Antenna Gain and MODCODES







Ka-band Achievable Data Rates vs. Spacecraft Antenna Gain and MODCODES



