https://ntrs.nasa.gov/search.jsp?R=19700015905 2018-07-25T13:08:58+00:00Z

N 70 25214 0
NASA CR 108434

Office of Naval Research
Contract N00014-67-A-0298-0006 NR-372-012

NATIONAL AERONAUTICS AND SPACE ADMINISTRATION
Grant NGR 22-007-068

QUALITATIVE APPLICATION OF A RESULT IN CONTROL THEORY TO PROBLEMS OF ECONOMIC GROWTH

CASE FILE COPY

By

Milind M. Lele, David H. Jacobson and James L. McCabe

December 1969

Technical Report No. 602

This document has been approved for public release and sale; its distribution is unlimited. Reproduction in whole or in part is permitted by the U. S. Government.

Division of Engineering and Applied Physics
Harvard University • Cambridge, Massachusetts

Office of Naval Research

Contract N00014-67-A-0298-0006

NR-372-012

National Aeronautics and Space Administration

Grant NGR 22-007-068

QUALITATIVE APPLICATION OF A RESULT IN CONTROL THEORY TO PROBLEMS OF ECONOMIC GROWTH

By

Milind M. Lele, David H. Jacobson, and James L. McCabe

Technical Report No. 602

This document has been approved for public release and sale; its distribution is unlimited. Reproduction in whole or in part is permitted by the U. S. Government.

December 1969

The research reported in this document was made possible through support extended the Division of Engineering and Applied Physics, Harvard University by the U. S. Army Research Office, the U. S. Air Force Office of Scientific Research and the U. S. Office of Naval Research under the Joint Services Electronics Program by Contracts N00014-67-A-0298-0006, 0005, and 0008 and by the National Aeronautics and Space Administration under Grant NGR 22-007-068.

Division of Engineering and Applied Physics

Harvard University · Cambridge, Massachusetts

QUALITATIVE APPLICATION OF A RESULT IN CONTROL THEORY TO PROBLEMS OF ECONOMIC GROWTH

By

Milind M. Lele, David H. Jacobson, and James L. McCabe*

Division of Engineering and Applied Physics

Harvard University · Cambridge, Massachusetts

ABSTRACT

Recent investigations into necessary conditions of optimality for control problems with inequality constraints on the state variables have shown that, for a specific class of problems, the optimal trajectory does not stay on the constraint boundary for non-zero intervals of time. This result permits, *a priori*, some insight into the structure of the optimal solution.

For certain problems in growth economics, this result is of some significance, as is shown by three examples from two different areas. The first two examples are concerned with the problem of optimal employment; interestingly enough, they indicate that, for the models used, the optimal solution is such that full employment is attained at most instantaneously and is not maintained for non-zero intervals of time. The third example is concerned with the optimal investment and foreign aid policies for an underdeveloped economy. An institutional constraint on the stock of foreign debts may be derived from the 'debt-service' ratio. It appears that, contrary to earlier results obtained from simpler models, this constraint is binding at most instantaneously along the optimal trajectory.

---

*Agency for International Development.

1. Introduction

Optimal control problems with inequality constraints on the state variables have been the subject of much research in the past decade. Necessary conditions of optimality for the first order case†, i.e. where the first time derivative of the constraint contained the control variable explicitly, were obtained by Gamkrelidze [1] in 1960. Later researchers extended these to the general case where the order of the constraint, p, was greater than one. Recently, Jacobson, Lele and Speyer [2] have obtained sharper results for this general case, than those known heretofore. (This reference also contains a brief history of earlier research.) A consequence of the new necessary conditions of optimality is that, under certain conditions, problems with odd-ordered constraints -- except the case $p = 1$ -- will not, in general, exhibit optimal trajectories with boundary arcs over non-zero intervals of time, i.e. the optimal trajectory will at most only touch the constraint boundary, but will not lie along it.

The significance of this result lies in the fact that, inasmuch as the conditions under which it is valid are not overly stringent, it reveals, *a priori*, considerable information as regards the structure of the optimal solution. It is our opinion that such information would be of particular qualitative value in problems of economic growth. To this end, after presenting a brief summary of the relevant control-theoretic results, we will consider three examples from economic growth theory. Two of these examples deal with the problem of optimal employment; the third is drawn from development planning.

---

†A state-variable inequality constraint is pth order if its pth time derivative is the first to contain the control variable explicitly.

2. Summary of Results from Control Theory

We briefly summarize the results which we will be using from control theory. The details are given in [2].

For simplicity, the basic optimization problem which we consider is in the form of Mayer. There is, however, no loss of generality, so that we are at liberty to apply these results to other formulations.†

The basic problem is

$$\underset{u}{\text{Maximize}}\ \Phi(x(T)) \tag{1}$$

subject to

$$\dot{x}(t) = f(x(t), u(t))\ ; \qquad x(0) = x_o \tag{2}$$

and the scalar state variable inequality constraint

$$S(x(t)) \leqslant 0 \qquad \text{for all } t \in [0, T] \quad . \tag{3}$$

Here

x -- n-dimensional state-vector

u -- scalar control variable

f -- n-dimensional vector function

S -- pth order state variable constraint

Φ -- scalar function of the terminal state

$(\dot{\ }) \equiv \frac{d}{dt}$

The necessary conditions of optimality for the above problem are given by the following theorem, which we state without proof. (For proofs of this and other theorems, see [2]).

---

†For relations between this and other formulations, see Bryson and Ho [3].

Theorem 1. The necessary conditions of optimality for the basic problem are

$$\frac{\partial H}{\partial u} = 0 = f_u^T \lambda \tag{4}$$

$$-\dot{\lambda} = \left\{ \begin{array}{l} \dfrac{\partial H}{\partial x} \\ \\ f_x^T \lambda + \eta S_x \end{array} \right\} \quad \lambda(T) = \left. \frac{\partial \Phi}{\partial x} \right|_T \tag{5}$$

where

$$\eta(t) = \begin{cases} \leqslant 0 & S(x(t)) = 0 \\ 0 & S(x(t)) < 0 \end{cases} \tag{6}$$

is a bounded function for $t \in [0, T]$.

At junction points t_i of boundary and interior arcs, the influence functions $\lambda(t)$ may be discontinuous. The boundary conditions are

$$\lambda(t_i^+) = \lambda(t_i^-) - \nu(t_i)\left(\frac{\partial S}{\partial x}\right)_{t_i} \tag{7}$$

and

$$H(t_i^+) = H(t_i^-) \tag{8}$$

where $\nu(t_i) \leqslant 0$. The Hamiltonian H used above, is defined by

$$H \equiv H(x, u, \lambda) = \eta S + \lambda^T f \quad . \tag{9}$$

The assumptions made in the derivation of these necessary conditions are given in [2]; the only noteworthy assumption is that

$$\frac{\partial}{\partial u} \left[\frac{d^p}{dt^p} (S(x(t))) \right] \neq 0 \tag{10}$$

i.e. that along the constraint boundary small changes in control can be related uniquely to small changes in the state variables; this is a common assumption [3].

Before proceeding further, let us make the

Definition: The Hamiltonian H, is said to be regular along an extremal if it possesses a unique maximum with respect to the control at every instant in time.

Note that the Hamiltonian H, is really $H(x, u, \lambda)$. The above definition requires that for all $t \in [0, T]$, given the extremal trajectories (say) $\bar{x}(t)$, $\bar{\lambda}(t)$, $H(\bar{x}, \bar{\lambda}, u)$ have a unique maximum with respect to $u(t)$. This does not exclude the possibility of multiple, non-neighboring, extremals, along each of which the Hamiltonian may still be regular i.e. does not exclude problems having multi-maximums. So the imposition of regularity on the Hamiltonian is not a very stringent requirement on the control problem.†

If now, we impose the additional restriction that the Hamiltonian be regular, it can be shown [2] that the optimal control variable u, as well as its p - 1 time derivatives must be continuous. Furthermore, a rather simple expression can be obtained for the entry-point multiplier, ν. We have,

Theorem 2. If the Hamiltonian is regular, $S \in B_{2p-1}[0, T]$‡ and the extremal path has a boundary arc of non-zero length, then

$$\nu(t_1) = \frac{(-1)^p H_{uu}^- [\overset{p-1}{(u)}^- - \overset{p-1}{(u)}^+]^2}{\overset{2p-1}{(S)}^-} \tag{11}$$

where $(\ )^-$ denotes $(\ )$ on the interior arc at the junction time t_1.

---

†In point of fact, it is rather difficult to construct a non-regular Hamiltonian e.g. see [3] p. 126.

‡$B_{2p-1}[0, T] \equiv$ class of functions whose (2p - 1)th derivative is bounded in the interval [0, T].

This expression for the entry point multiplier is very significant. Note that $H^-_{uu} < 0$ (strengthened necessary condition for H to have a maximum), $[\overset{p-1}{(u)}^- - \overset{p-1}{(u)}^+]^2 \geqslant 0$, and as S and its time derivatives up to $d^{2p-1}/dt^{2p-2}(S)$ are continuous (therefore zero)

$$\overset{2p-1}{(S)}^- > 0 \tag{12}$$

in order for the trajectory to reach the boundary. This implies that

$$\nu(t_1) \geqslant 0 \tag{13}$$

for p odd. But $\nu(t_1) \leqslant 0$ (necessary condition of optimality) and hence (13) implies that for odd-order constraints, the optimal trajectory will, at most, only touch the constraint boundary, provided $\overset{p-1}{(u)}^- \neq \overset{p-1}{(u)}^+$.† Note that for p = 1, it can be shown that (see [2] p. 23) $\nu(t_1) = 0$; thus for first order constraints boundary arcs <u>are possible</u>.

3. Employment Model A

The first example deals with the imposition of a subsidy for employing additional laborers where the marginal product of labor is already equal to the minimum wage. Assume that the neo-classical theory of the firm holds; in particular, that the long-run ratio of labor demanded to capital demanded may be determined by differentiating the production function and setting the ratio of the partial derivatives equal to the factor price ratio. The production function in this case is Cobb-Douglass with constant returns to scale (homogeneous of degree one). Suppose further that the demand for capital is equated to the capital actually used but that labor demanded and labor employed are not necessarily

---

†The case $\overset{p-1}{(u)}^- = \overset{p-1}{(u)}^+$ is possible, but numerical experience with problems ($p \geqslant 3$) indicates that this is rare. In fact x_o would have to be carefully chosen for this to occur.

identical, then we may express the ratio of labor demanded to capital in use by the equation

$$\left(\frac{D}{K}\right) = \left(\frac{1 - \alpha}{\alpha}\right)\left(\frac{r}{w}\right) \tag{14}$$

where $\left(\frac{r}{w}\right)$ is the interest wage ratio, D is the labor demanded, K is the value of the capital stock in use, and α is the capital elasticity of the output.

The term on the r.h.s. of (14) must be complicated a bit when we allow for the presence of government tax policies and subsidies, and the effect of lagged responses to changes in the effective factor price ratio. Consider first the tax adjustment coefficient for the interest rate. This coefficient is defined by the equation

$$h = \frac{(1 - \beta)}{(1 - u_c)} \tag{15}$$

where β is the amount of the investment tax credits and depreciation deductions expressed as a percentage of the gross investment and u_c is the tax rate on capital income. A similar relationship may be defined for the wage adjustment coefficient v. Here we assume that the firm does not pay a tax on the labor it employs and that the coefficient represents a subsidy for the employment of additional laborers expressed as a percentage of the increment in the wage bill. The effective interest-wage ratio g may then be expressed as

$$g = \left(\frac{r}{w}\right)\left(\frac{h}{v}\right) \tag{16}$$

We wish to avoid specifying how factor prices are determined within the model. Therefore, we shall define the change in the effective factor-price ratio between time periods, $\dot{g}$, as our control variable rather than $\left(\frac{\dot{h}}{v}\right)$, i.e.

$$\dot{g} = u \ . \tag{17}$$

Brown and de Cani [4] and David and van de Klundert [5] have adduced reasons why the response to changes in factor prices may be considerably greater in the long-run, than in the short-run. The main point is that to introduce a new technology with different factor proportions may require a new machine; on existing machines, proportions may be fixed. Given that the lag structure is one with geometrically declining weights†, the equation for desired factor proportions may be written as

$$\left(\frac{D}{K}\right)_t = \left(\frac{1-\alpha}{\alpha}\right) \sum_{i=0}^{\infty} (1-\lambda)\lambda^i g_{t-i} \tag{18}$$

where λ $(0 < \lambda < 1)$ is the initial weight. As Koyck [6] has demonstrated, a reduced form of this relationship may be obtained. Lag the equation one period, multiply it through by λ, and then subtract the lagged equation from (18). The procedure yields,

$$\left(\frac{D}{K}\right)_t = (1-\lambda)\left(\frac{1-\alpha}{\alpha}\right)g_t + \lambda\left(\frac{D}{K}\right)_{t-1} \tag{19}$$

This first order difference equation may be approximated by the first order differential equation. (For an alternative procedure, see Grilliches [7].)

$$\frac{d}{dt}\left(\frac{D}{K}\right) = m_1\left(\frac{1-\alpha}{\alpha}\right)g - m_2\left(\frac{D}{K}\right) \tag{20}$$

$(0 < m_1,\ 0 < m_2 < 1$. In what follows all coefficients are positive constants, unless otherwise stated.)

There is a distinct difference between the change in the effective interest-wage ratio (Δg) and the final change in that ratio which equates

---

†Estimates, using this form of the lag structure, have been carried out in [4], [5] for the more general c.e.s. production function.

demand and supply for labor, (Δg^*). In the short-run, changes in the technical labor requirements may produce a slow response from the supply side. There may not be enough laborers with the requisite skills in times of excess demand, and training may be necessary; in times of deficit demand, firms may retain their skilled personnel. Also, the empirical evidence suggests that labor force participation rates, while positively correlated with employment, tend to lag fluctuations in employment. Finally, the firms may anticipate a future change in demand opposite to the one that has just occurred. Under these circumstances, they may concentrate on meeting their demand for production workers and not overhead personnel†.

Rather than determine an equilibrating change in the effective interest-wage ratio, we choose to represent these bottlenecks by an adjustment equation

$$L_t = p[D_t - L_{t-1}] + L_{t-1} \qquad 0 < p < 1 \tag{21}$$

where L_t is the level of employment attained in period t. This is approximated by the first order differential equation

$$\frac{d}{dt}(L) = \eta_1 D - \eta_2 L \quad . \tag{22}$$

The remaining dynamic equation concerns the growth of capital stock over time. Given a Cobb-Douglass production function with constant returns to scale, value added is given by

$$v_t = K_t^{a} \varsigma_t^{1-a} \tag{23}$$

where

$$\varsigma_t = \text{minimum } [L(t), D(t)] \quad . \tag{24}$$

---

†Most of these arguments, along with the empirical evidence supporting them, are given in Kuh [8].

Suppose that saving is expressed as a constant proportion of value added, then the capital accumulation equation is

$$\frac{d}{dt}(K) = sK^{\alpha}\zeta^{1-\alpha} - \delta K \tag{25}$$

where s is the constant average propensity to save and δ is the rate of depreciation.

The state variable L(t) is constrained below by zero† and above by the full-employment ceiling (given exogenously) $\overline{L}(t)$; i.e.

$$0 \leqslant L(t) \leqslant \overline{L}(t)^{\ddagger}, \qquad t \in [0, T] \quad . \tag{26}$$

Finally, denoting the termination date by T, the rate of social discount by γ, the control variable cost coefficient by σ, we may write the welfare functional which we wish to maximize, in the form

$$J = \int_0^T e^{-\gamma t}[(1 - s)K^{\alpha}\zeta^{1-\alpha} - \sigma u^2]dt \quad . \tag{27}$$

The first term in the welfare functional represents consumption‡; this is a familiar component of aggregate welfare. But why, one may ask, is there control variable costing? The answer is that changes in the control may be expensive in the sense that risk may be increased and speculative behavior on the part of the firm may result. (Perhaps the reason that "control costing" of this form has not been used earlier is that models with high-order dynamics, where such costing is appropriate, have been rarely considered in the literature on growth theory.)

---

†The lower ceiling on L(t) is of little economic significance.

‡$\overline{L}(t)$ will be assumed to be monotone increasing.

‡More correctly, this should be modified to include per capita consumption. However, this does not affect our results.

Gathering together the dynamics, along with the welfare functional (27) and the state-variable inequality constraint (26), optimal employment is given by the following maximization problem:

$$\text{Max } J = \int_0^T e^{-\gamma t}[(1 - s)K^{\alpha}\zeta^{1-\alpha} - \sigma u^2]dt \tag{28}$$

subject to

$$\dot{g} = u \tag{29}$$

$$\dot{\left(\frac{D}{K}\right)} = m_1\left(\frac{1-\alpha}{\alpha}\right)g - m_2\left(\frac{D}{K}\right) \tag{30}$$

$$\dot{L} = \eta_1 D - \eta_2 L \qquad (1 > \eta_1 > \eta_2 > 0) \tag{31}$$

$$\dot{K} = sK^{\alpha}\zeta^{1-\alpha} \tag{32}$$

where ζ[†] is given by (24), and initial conditions on the state variables are specified (T is fixed); and subject to the third order state constraint

$$0 \leqslant L(t) \leqslant \overline{L}(t) \quad . \tag{33}$$

4. Employment Model B

Let us now turn to a situation in which the obstacle to full employment is not a floor on the real wage but insufficient training of workers. Dobell and Ho [9] have formulated a model which deals with this set of circumstances. It centers around a well-behaved production function with constant returns to scale

$$V = F(K, W) \tag{34}$$

where K is the stock of machinery and W is the stock of trained workers. Denote the flow of educational services by E, gross additions to machinery

---

[†]The Hamiltonian is still piecewise continuous and differentiable. See Appendix I.

by M, and consumption by C. Then according to Dobell and Ho [9] we may write

$$V = M + C + E \tag{35}$$

as an accounting identity.

Dobell and Ho go on to argue that this identity may be used as a transformation surface; this appears to be a simplified model. It implies that resources may be shifted instantaneously from one form of production to another with no loss in the total value of services rendered. However, time may be required for retraining of workers and for the restructuring or retirement of machines. Even in the case of an increment in V, the planning authority would have to exert considerable control over vocational choice and the bill of new machines to achieve a relationship independent of past production.

Let us remedy this lack of realism with a simple modification of the Dobell-Ho model. Denote the ratio of educational services to total value added by $z = \frac{E}{V}$. Then postulate a relationship involving a delayed adjustment

$$z_t = p[z_t^* - z_{t-1}] + z_{t-1} \qquad 0 < p < 1 \tag{36}$$

where z_t^* is the desired ratio of educational services to value added. We will write z_t^* as

$$z_t^* = u_1 \tag{37}$$

where $u_1(t)$ is a control variable. Then, approximating (36) by a differential equation, we have

$$\dot{z} = \pi_1 u_1 - \pi_2 z \tag{38}$$

where $0 < \pi_1 < 1$, $0 < \pi_2 < 1$.

Delays in the shifting of resources between machinery and consumption goods production only complicate the problem without affecting the

end result. Therefore, in the case of machinery, neglecting depreciation, we may write

$$\dot{K} = M \quad . \tag{39}$$

Dobell and Ho specifically mention that they neglect gestation lags in the training of workers. Assuming that the rate of worker retirement is zero (for simplicity), their equation for the level of educational services is

$$E_t = d(W_{t+1} - W_t) \tag{40}$$

where W is the level of employment. The coefficient d they assume to be an increasing function of the employment rate 'W/I', where I is an exogenously given full employment rate.† Let us make d a constant independent of the employment rate, and denote the desired change in the trained labor force between periods t and t + 1 by

$$\Delta W_t^* = \frac{1}{d} E_t \quad . \tag{41}$$

Then, given a lag structure with geometrically declining weights, the change in the trained labor force may be expressed as

$$\Delta W_t = (1 - \lambda_1) \sum_{i=0}^{\infty} \lambda_1^i \, \Delta W_{t-i}^* \tag{42}$$

Again, following [6], [7], this equation reduces to

$$\Delta W_t = \frac{1}{d}(1 - \lambda_1)E_t + \lambda_1 \, \Delta W_{t-1} \quad . \tag{43}$$

---

†In [10] Dobell and Ho consider the case of a constant training cost. For this case, their results unequivocally yield sustained full employment for a significant portion of the optimal trajectory. The case of an increasing training cost gives the solution discussed in [9].

We approximate this second order difference equation with the differential equation

$$\ddot{W} = \mu_1 E - \mu_2 \dot{W} \qquad 0 < \mu_1 , \mu_2 < 1 \tag{44}$$

The dynamic equations for our system are (38), (39) and (44). For convenience, we will re-write these equations in a normalized form, assuming that the total labor force grows at an exponential rate n $(0 < n < 1)$ i.e.

$$\overline{L} = L_o e^{nt} \qquad L_o = \text{initial value} \tag{45}$$

Define

$$\frac{W}{\overline{L}} = \omega \tag{46}$$

$$\frac{K}{\overline{L}} = k \tag{47}$$

$$\frac{M}{V} = u_2 \qquad \underline{\text{control variable}} \tag{48}$$

$$\frac{C}{V} = c \tag{49}$$

and

$$F(\frac{K}{\overline{L}}, \frac{W}{\overline{L}}) = \frac{V}{\overline{L}} = f(k, \omega) \quad . \tag{50}$$

Then (38), (39) and (44) may be written as

$$\dot{z} = \pi_1 u_1 - \pi_2 z \tag{51}$$

$$\dot{k} = -nk + u_2 f(k, \omega) \tag{52}$$

and

$$\ddot{\omega} = \mu_1 z f(k, \omega) - (\mu_2 + 2n)\dot{\omega} - n(n + 1)\omega \quad . \tag{53}$$

In addition to the full employment ceiling on ω,

$$0 \leqslant \omega \leqslant 1 \quad , \tag{54}$$

the identity (35) gives the following constraints on z and u_2;

$$0 \leqslant z \leqslant 1 \tag{55}$$

$$0 \leqslant u_2 \leqslant 1 \tag{56}$$

$$0 \leqslant u_2 + z \leqslant 1 \quad . \tag{57}$$

The welfare functional which we wish to maximize consists of the discounted per capita consumption stream less penalty terms (which reflect our desire for some stability in policy). Summarizing, optimal employment is obtained by maximizing the welfare functional

$$J = \int_0^T e^{-\gamma t}[(1 - z - u_2) f(k, \omega) - \sigma_1(\pi_1 u_1 - \pi_2 z)^2 - \sigma_2(u_2 - b(t))^2]dt \tag{58}$$

with the dynamics

$$\dot{z} = \pi_1 u_1 - \pi_2 z \tag{59}$$

$$\dot{k} = -nk + u_2 f(k, \omega) \tag{60}$$

$$\dot{\omega} = y \tag{61}$$

and

$$\dot{y} = \mu_1 z\, f(k, \omega) - (\mu_2 + 2n)y - n(n + 1)\omega \tag{62}$$

and subject to the constraints

$$0 \leqslant \omega \leqslant 1 \qquad \text{(third order state constraint)} \tag{63}$$

$$0 \leqslant z \leqslant 1 \tag{64}$$

$$0 \leqslant u_2 \leqslant 1 \tag{65}$$

$$0 \leqslant u_2 + z \leqslant 1 \quad . \tag{66}$$

Before going on to discuss the implications of this model along with those of model A, we note the following:

i) As the proportion of resources devoted to education changes there may be increasing opportunity costs; thus a quadratic penalty is applied to $\dot{z}$.

ii) The penalty term $-\sigma_2(u_2 - b(t))^2$ reflects our desire for a stable policy of investment. Absence of such a term would lead to 'bang-bang' solutions; such solutions are not economically very meaningful. The presence of the penalty reflects the desire for some mean rate of machinery investment, b(t), and the possibility of increasing opportunity costs when resources are shifted into machines.

iii) Some consideration should also be given to the terminal conditions in both models A and B. We have not done so for this would not change our qualitative results. This is, however, certainly a point to remember in computing solutions.

5. Discussion of Models A and B

The constraints on the state variables representing the employment level in both models A and B are third order (odd order). Before applying Theorem 2, however, we must verify if the problems satisfy the conditions imposed therein.

In both models A and B, the Hamiltonians are regular. In model A, the term $\zeta(t) = \min(D, L)$, does not prevent the application of Theorem 2, as shown in Appendix I; we assume $\overline{L}(t)$ to be sufficiently differentiable. In model B, the presence of constraints on u_2 and z apart from that on ω, makes for added complexity. We show in Appendix II that these constraints do not affect our conclusions provided $\mu_2^2 > 4n(1 - \mu_2)$.†

With these preliminaries, we can now state our central result for both problems: From Theorem 2 (and Appendix II) the characteristic of the optimal employment path is that:

---

†This is not an overly stringent condition if education in the model is defined as short-term vocational training. Other educational services may be expressed as an exogenous component of E without affecting the end result.

full employment is attained, at most, instantaneously, i.e. full employment is not maintained for non-zero intervals of time.

Note that in model B, the cost of training has been assumed to remain constant as the employment level rises. By contrast, the example discussed by Dobell and Ho in [9] does not exhibit full employment along the optimal trajectory due to increasing training costs; whereas their constant training cost model of [10] exhibits sustained full employment. In both our models A and B it is the lag structure (i.e. the order of the constraint) alone that causes sustained full employment to be non-optimal.

What are the policy implications of our two employment models? If the problems were re-formulated so that $\dot{L}$ or $\dot{\omega}$ was controlled directly, the employment level would move to its upper bound and stay there. Unequivocally, the integral of the discounted consumption stream would be larger in the case of model A (provided there is no control variable costing) than it is in the original case with the third order constraint; for value added, and hence consumption, is an everywhere increasing function of employment.

How effective the planning authorities can be in eliminating delays remains unclear. But some possibilities do exist. One is subsidized on-the-job training. Employment model B may depend too heavily on the assumption that a threshold level of skill must be achieved before hiring can be justified. On-the-job training may be less efficient from a production standpoint, but it still affords the possibility of optimal full employment. Training is conducted as part of the education process; thus an instantaneous transfer of resources into education may be plausible.

Further, there is flexibility in the skill level required for employment. Whether or not it is optimal to substitute this scheme for slower training procedures is still open to question.†

6. A Model of Foreign Debt

In the study of developing nations, it is interesting to evaluate the optimal accumulation path of foreign debt over time. Here mounting interest costs must be balanced against the increased capital accumulation and imports which an inflow of foreign loans permits.

Our model centers around four dynamic equations. Let us first consider the investment-demand equation.

Assume again that total value added is given by a Cobb-Douglass production function with constant returns to scale. The price of traded and domestically produced goods is the same. The level of employment is constant, and the units in which labor is expressed may be normalized to equal one. Then, following the principles of optimality for the firm, the desired level of capital stock K_t^* may be derived from the condition that the value of the marginal product of capital should be equal to the rental price of capital; for a Cobb-Douglass production function this gives:

$$K_t^* = \frac{\alpha K^{\alpha}}{z_t} \tag{67}$$

where z_t is the real rate of interest multiplied by a tax adjustment coefficient like the one in (15), and α is the capital elasticity of output.‡

---

†Dobell [11] discusses a model which permits reductions in the extent of training as a means of offsetting rising training costs, rather than as a method of reducing the gestation lag in training. In this model it is optimal to achieve full employment.

‡This discussion borrows heavily from the work of Jorgenson [12].

On the basis of a 'putty-clay' model of the firm, Bischoff [13] has shown that the response of investment to changes in relative prices is more delayed than its response to output. Therefore, let us divide the demand for investment, I^*, into two parts: that due to output changes I^*_v, and that due to interest changes I^*_z. Assume that there is no demand lag in reaction to variations in output. Then we may approximate I^*_v as

$$I^*_v = \frac{a^2 K^{a-1}}{z} \cdot \frac{d}{dt}(K) \quad . \tag{68}$$

The capital accumulation equation is

$$\dot{K} = I - \delta K \tag{69}$$

where I is gross investment and δ is the rate of depreciation.

On the other hand, I^*_z depends on past as well as present changes in the real rate of interest, z. With a lag structure involving geometrically declining weights, this can be expressed as

$$(I^*_z)_t = (1 - \lambda')(\Delta K^*_z)_t + \lambda'(I^*_z)_{t-1} \tag{70}$$

where $(\Delta K^*_z)_t$ is the change in the desired capital stock between time periods t - 1 and t due to a change in z. This is approximated by the first order differential equation

$$\dot{I}^*_z = \eta_1 \frac{aK^a}{z^2} \dot{z} - \eta_2 I^*_z \tag{71}$$

The control variable is defined by the equation

$$\dot{z} = u \quad . \tag{72}$$

Thus far, nothing has been said about the lag in supply; this brings us to the third dynamic equation. Generally there is a considerable length of time between the ordering of machines and structures and their availability. Specifying this gestation lag as one with geometrically declining weights, we determine current gross investment with the function

$$I_t = (1 - \lambda_2)I_t^* + \lambda_2 I_{t-1}^* + \delta_1 K_t \tag{73}$$

which we approximate by the differential equation

$$\dot{I} = \mu_1 I^* - \mu_2 I + \mu_3 K \quad . \tag{74}$$

Recognising that $I^* \equiv I_z^* + I_v^*$ and using (68) we have for I

$$\dot{I} = \mu_1 [I_z^* + \frac{a^2 K^{a-1}}{z} (I - \delta K)] - \mu_2 I + \mu_3 K \quad . \tag{75}$$

The control u enters through $\dot{I}_z^*$; hence we control not $\dot{I}$ but $\ddot{I}$.

The last dynamic equation concerns the growth in foreign debt. Net foreign capital inflow is the difference between gross investment and gross domestic saving. Let V represent gross domestic product, and assume that gross domestic savings S may be expressed as a linear function of V (= K^a)

$$S = sK^a - b \tag{76}$$

where s is the aggregate (constant) savings rate. Substituting this into the identity for net foreign capital inflow and subtracting off interest payments from savings yields

$$\dot{D} = I - sK^a + b + fD \tag{77}$$

where D is foreign debt, and f represents interest payments as a proportion of foreign debt.

An explicit balance of payments equation is neglected. Imports, it is presumed, are allowed to vary so as to always equal the sum of exports and net capital inflow. We note that creditor nations tend to scrutinize the ratio of total debt service payments to export earnings, the 'debt-service ratio'.† Suppose that debt-service payments may be

---

†See, for example, Avramovic [14].

represented as a fixed proportion, θ, of total debt and that export earnings $\overline{E}$ are taken as exogenous. Then, we assert, no more loans will be forthcoming once debt-service payments reach a certain percentage, β, of export earnings. Symbolically

$$\theta D(t) \leqslant \beta \overline{E}(t) \tag{78}$$

i.e. a constraint on the debt level.

In this model the welfare functional which is to be maximized is

$$J = \int_0^T e^{-\gamma t}[\{(1 - s)K^{\alpha} + b\} - \sigma u^2]dt \tag{79}$$

subject to (69), (71), (72), (75), (77) and (78). Here T is the planning horizon and γ is the rate of social discount. (The remarks of the footnote on page 9 regarding per capita consumption also apply.) The main component of the integrand is consumption which is determined by subtracting savings from gross domestic product. For the reasons cited earlier, we penalize changes in the control variable with the coefficient σ. Some allowance should also be made for the effect of tax policy on income distribution. This effect is not accounted for as it is difficult to do so without explicitly determining the rate of interest.

In sum, the optimal debt policy is given by the following optimization problem.

$$\underset{u}{\text{Maximize}}\ J = \int_0^T e^{-\gamma t}[\{(1 - s)K^{\alpha} + b\} - \sigma u^2]dt \tag{80}$$

subject to

$$\dot{z} = u \tag{81}$$

$$(\dot{I}_z^*) = \eta_1 \frac{\alpha K^{\alpha}}{z^2} u - \eta_2 I_z^* \tag{82}$$

$$\dot{I} = \mu_1[I_z^* + \frac{a^2K^{a-1}}{z}(I - \delta K)] - \mu_2 I + \mu_3 K \tag{83}$$

$$\dot{K} = I - \delta K \tag{84}$$

and

$$\dot{D} = I - sK^a + b + fD \tag{85}$$

and subject to the third order state constraint

$$\theta D(t) \leqslant \beta \overline{E}(t) \tag{86}$$

with specified initial and terminal conditions on the five state variables.

As the Hamiltonian for the above problem is regular, we have by Theorem 2 that:

<u>The optimal debt level touches the debt-service ratio ceiling at most instantaneously i.e. optimal debt level is not maintained equal to the debt-service ratio ceiling for a non-zero time interval.</u>

There is a significant contrast between the optimal path in our model and the 'bang-bang' solutions of Chenery and MacEwan [15] and Cetin and Manne [16]. The latter models are linear programs; upper bounds are placed either on the change in investment or the net change in the level of debt. These constraints are continuously binding in the early periods of the solutions. Considering the general structure of both models, this is equivalent to saying that the constraints on maximum debt are binding in each of the initial periods. Yet, we know from the order of the constraint in our model that the debt level touches its upper bound at most instantaneously. Consequently, the nature of the optimum debt path for higher order models (which are perhaps more realistic) is considerably more complex than past programming results suggest.

Given a lower order constraint on D(t), i.e. more direct control of the debt level, and no costing on the control, the economy is better off growing along the upper bound on debt than it is in meeting the optimality conditions in the third order constrained model. In calculating the social cost of discarding capital, the possible social benefits of eliminating the lagged demand must be netted out. Thus, because firms do not consider this effect in their cost calculations, subsidized discarding of capital may be justified under some circumstances. For the delay in the response of investment demand to changes in the effective interest rate may be reduced. Obviously, such tradeoffs can only be examined in the context of larger models.

7. Conclusions

We have shown that there exist economic growth problems, with constraints on the state variables, where some qualitative features of the optimal trajectories may be deduced a priori, if the order of the constraint is odd (but not one). The empirical validity of geometrically declining weights for the lag functions -- an assumption upon which many of our differential equations rely -- is perhaps questionable.† But few would deny that some form of lag structure exists. This, together with our results, suggests that decision rules based on systems not incorporating these lag structures must be held suspect.

Thus in this sense, our main contribution has been negative. Let us now outline some possible areas for future research.

What are the properties of the optimal employment trajectory beyond its touching the full employment bound at most instantaneously?

---

†However, see Grilliches [7] with regard to other estimates.

Clearly, the policy implications differ radically depending upon whether or not the state variable path is cyclical in nature, i.e. bounces on and off the full employment bound. In situations where a certain level of unemployment is optimal, it may be desirable to use income redistribution policy to compensate the unemployed (e.g., "a guaranteed annual income"). But for an optimal trajectory which is cyclical, the timing of such a policy would be critical; thus, in this case redistribution of income may be intractable in view of the institutional inflexibilities of fiscal policy. For an optimal trajectory which touches only in the terminal period, if at all, a slow implementation of policies may be considerably less serious.

Past programming results ([15] and [16]) indicate that it may be extremely costly to employ periodic limits on accumulated foreign debt other than the usual terminal condition. Our analysis throws no light on the expense inherent in the imposition of the state variable constraint. Nor do we have any indication of the number of times, if at all, the service payments strike their upper bound. These are crucial issues. Take, for instance, the case where the upper bound on service payments coincides with the terminal requirement at that point in time. If it could be established that the state variable constraint is binding only in the terminal period, then considerable support would be given to the institutionalized system of debt allocation where a given debt-service ratio is not exceeded. Insight into these problems may well come from numerical solutions.

8. Acknowledgements

The authors would like to thank Professor Kenneth J. Arrow for his valuable suggestions.

References

1. Gamkrelidze, R. V., "Optimal processes with bounded phase coordinates," Izv. Ahad. Nank, USSR, Sec. Mat., vol. 24, pp. 315-356, 1960.

2. Jacobson, D. H., M. M. Lele and J. L. Speyer, "New necessary conditions of optimality for control problems with state-variable inequality constraints," Technical Report No. 597, Div. of Engg. and App. Physics, Harvard University, August 1969.

3. Bryson, A. E. Jr., and Y. C. Ho, "Applied Optimal Control," Blaisdell Publishing Co., Waltham, Mass., 1969.

4. Brown, M. R., and J. S. de Cani, "Technological change and the distribution of income," International Economic Rev., vol. 4, No. 3, pp. 289-309, Sept. 1963.

5. David, P. A., and Th. van de Klundert, "Biased efficiency growth and capital labor substitution in the U.S. 1899-1960," American Economic Review, June 1965, pp. 357-394.

6. Koyck, S. M., "Distributed lags and investment analysis," North-Holland Publishing Co., Amsterdam, 1954.

7. Grilliches, Zvi, "Distributed Lags: A Survey," Econometrica, vol. 35, No. 1, pp. 16-49, January 1967.

8. Kuh, Edwin, "Measurement of potential output," American Economic Rev., pp. 758-777, September 1966.

9. Dobell, A. R., and Y. C. Ho, "An Optimal Unemployment Rate," Quarterly Journal of Economics, November 1967.

10. Dobell, A. R., and Y. C. Ho, "Optimal Investment Policy: A Control Problem in Economic Theory," IEEE Trans. on Autom. Control, vol. AC12, No. 1, pp. 4-14, February 1967.

11. Dobell, A. R., "An Optimal Employment Rate (Reply)," Quarterly Journal of Economics, vol. 83, No. 3, pp. 521-523, August 1969.

12. Jorgenson, D. W., "Capital Theory and Investment Behavior," American Economic Review, vol. 53, No. 2, 1962.

13. Bischoff, C., "Elasticities of substitution, capital malleability and distributed lag investment functions," to be published by The Brookings Institution as part of a conference on tax credits.

14. Avramović, Dragoslav, "Economic growth and external debt," Economics Department, International Bank for Reconstruction and Development, Baltimore, Johns Hopkins Press, 1964.

15. Chenery, H. B., and A. MacEwan, "Optimal Patterns of Growth and Aid: The Case of Pakistan," Chapter 6 in "The Theory and Design of Economic Development," edited by I. Adelman, and E. Thorbecke, Johns Hopkins Press, Baltimore, Md., 1966.

16. Cetin, H., and A. S. Manne, "A Dynamic Five-sector Model for Turkey, 1967-82," Stanford University Research Center in Economic Growth, Memo No. 61, June 1968.

Appendix I

Lemma: The Hamiltonian of employment model A is continuous and piecewise differentiable, except at points $t_i \in [0, T] \ni D(t_i) = L(t_i)$.

Proof: The only (possibly) non-differentiable function is

$$\xi(t) = \min[D(t), L(t)]$$

But D(t), L(t) are continuous and differentiable on [0, T]. Hence $\xi(t)$ is continuous and piecewise differentiable except (possibly) at $t_i \in [0, T] \ni$

$$D(t_i) = L(t_i)$$

where the derivative $\dot{\xi}(t)$ may not be continuous.

The discontinuities in $\dot{\xi}(t)$ will not affect the application of Theorem 2 provided they do not occur at $t_j\{\in[0, T]\}$ such that $L(t_j) = \overline{L}(t_j)$. That this is the case is seen if we re-write (31) in the form

$$\dot{L} = \eta_1(D - L) + (\eta_1 - \eta_2)L \quad .$$

Then, assuming that the initial value of L is less than $\overline{L}$, $\overline{L}(t_j) = \overline{L}(t_j)$ if and only if $D(t_j) > \overline{L}(t_j)$ (as $\eta_1 > \eta_2$ and $\eta_1 - \eta_2 < 1$). So the changeover $\xi(t) = L(t)[D(t)]$ from $\xi(t) = D(t)[L(t)]$ does not occur at t_j. The case when the initial value of L, $L(t_o)$, is equal to $\overline{L}(t_o)$ and $D(t_o) = L(t_o)$ $(= \overline{L}(t_o))$ causes no difficulties; for at $t = t_o + \epsilon$ $(\epsilon > 0)$

$$L(t_o + \epsilon) < L(t_o) = \overline{L}(t_o)^{\dagger} \quad .$$

So, if at t_o we set $\xi(t_o) = L(t_o)$, at time t $\xi(t)$ is still equal to L(t) [if $D(t) > L(t)$, if not set $\xi(t_o) = D(t_o) = L(t_o)$]. In either case, there is no changeover when $L(t) = \overline{L}(t)$.

$^{\dagger}\overline{L}(t)$ is assumed to be a monotone increasing function of time.

Appendix II

We have the following constraints [(63)-(66)]

$$0 \leqslant \omega \leqslant 1 \tag{II. 1}$$

$$0 \leqslant z \leqslant 1 \tag{II. 2}$$

$$0 \leqslant u_2 \leqslant 1 \tag{II. 3}$$

$$0 \leqslant u_2 + z \leqslant 1 \tag{II. 4}$$

Before we can apply Theorem 2, we must ensure that the presence of constraints (II. 2) - (II. 4) does not affect the continuity of u_1, u_2 and their derivatives.

Consider only (II. 2) - (II. 4). This gives rise to the seven cases:

A. z and u_2 both slack, $0 < u_2 + z < 1$.

B. z and u_2 both slack, $0 < u_2 + z = 1$.

C. $z = 0$, $u_2 = 0$, $u_2 + z = 0$.

D. $z = 0$, $0 < u_2 < 1$, $0 < u_2 + z < 1$.

E. $z = 0$, $u_2 = 1$, $u_2 + z = 1$.

F. $0 < z < 1$, $u_2 = 0$, $0 < u_2 + z < 1$.

G. $z = 1$, $u_2 = 0$, $u_2 + z = 1$.

We will now analyze each case individually.

A. No constraints effective. Then we can apply Theorem 2 directly.

B. u_2 and z slack; $u_2 + z = 1$. As z is slack, u_1 is given by

$$H_{u_1} = 0 = -2\sigma_1 u_1 + \pi_2 \lambda z \quad . \tag{II. 5}$$

Then

$$u_1 = \frac{\pi_2}{2\sigma_1} \lambda z \tag{II. 6}$$

and, assuming that f_k, f_ω exist -- a reasonable assumption -- u_1, $\dot{u}_1$ are continuous and $\ddot{u}_1$ exists. From $u_2 + z = 1$, $u_2 = 1 - z$; hence, u_2, $\dot{u}_2$, $\ddot{u}_2$

are continuous. We can now repeat the analysis (given in [2]) leading to the equation (11); this gives an expression for the multiplier ν_ω of the form

$$\nu_\omega = (-1)^p \frac{H^-_{u_1u_1}[(\ddot{u}_1)^- - (\ddot{u}_1)^+]^2 + H^-_{u_2u_2}[(\ddot{u}_2)^- - (\ddot{u}_2)^+]^2}{(S)^{2p-1}} \quad . \qquad \text{(II. 7)}$$

The second term on the r.h.s. is zero, but the first is not (except under very unusual circumstances). Thus we can apply a modified version of Theorem 2, and state that for this case $\omega = 1$ at most instantaneously.

Cases C, D and E can be treated together, for from the dynamic equations for ω and y, namely

$$\dot{\omega} = y \qquad \text{(II. 8)}$$

$$\dot{y} = \mu_1 f(k,\omega)\cdot z - (\mu_2 + 2n)y - n(n+1)\omega \qquad \text{(II. 9)}$$

we see that if $z = 0$, ω is governed by a homogeneous second order differential equation. For feasibility, if $\omega = 1$, $\dot{\omega} = y \leq 0$. So, provided $\mu_2^2 > 4n(1 - \mu_2)$ i.e. negative real eigenvalues, the trajectory will not stay on $\omega = 1$ except instantaneously.

F. z slack, $u_2 = 0$, $u_2 + z$ slack. This is further subdivided as follows: Let $\omega = 1$ at $t = t_1$ where condition F holds. Then either

i) u_2 has saturated prior to time t_1. In this case $\dot{u}_2$, $\ddot{u}_2$ exist and are continuous and the modification of Theorem 2 used in case B holds, and $\omega = 1$ only instantaneously.

ii) u_2 saturates at the same time, i.e. the transition from any of the other cases to this is made at time t_1. In this case as $\omega < 1$ prior to t_1 (we anticipate some of our analysis) we cannot unequivocally rule out the possibility of a sustained boundary arc in ω, i.e. $\omega = 1$ for a non-zero interval of time. Were this to be the case, however, the optimal solution would exhibit simultaneously

a. decreasing per capita capital stock

b. increasing per capita investment in education

c. decreasing per capita consumption.

Economically, this makes little sense; further an optimal solution exhibiting such a sustained arc would be (economically) indefensible. We thus conclude that we can safely rule out this possibility on purely economic grounds.

G. $z = 1$, $u_2 = 0$, $u_2 + z = 1$. Then u_2 must saturate prior to the time, t_1, at which $\omega = 1$ -- from continuity of $\dot{z}$ and $u_2 + z = 1$. This leaves only two possibilities

i) z saturates at the same instant, t_1

ii) z saturates <u>prior</u> to t_1.

In either case, subsequent to the time t_1, if the solution is to exhibit a sustained boundary arc in ω, the controls u_1, u_2 must satisfy

$$u_1 = \frac{\pi_2}{\pi_1} = \text{constant} \tag{II. 10}$$

$$u_2 = 0 \tag{II. 11}$$

and

$$\dddot{\omega} = 0 = \psi(u_1, u_2, t) \tag{II. 12}$$

But (II. 12) would require u_1 and u_2 to be time-varying, hence a boundary arc cannot be sustained.

Academy Library (DFSLB)
U. S. Air Force Academy
Colorado Springs, Colorado 80840

Hq. AFSC (SDTR)
Attn: Library/Documents
Arnold AFB, Tenn. 37389

Aeronautics Library
Graduate Aeronautical Laboratories
California Institute of Technology
1201 E. California Blvd.
Pasadena, California 91104

Aerospace Corporation
P. O. Box 95085
Los Angeles, California 90045
Attn: Library Acquisitions Group

Airborne Instruments Laboratory
Deerpark, New York 11729

AFAL (AVTA/R D. Larson)
Wright-Patterson AFB
Ohio 45433

AFCRL (CRMPLR)
AFCRL Research Library, Stop 29
L. G. Hanscom Field
Bedford, Mass. 01731

ADTC (ADBPB-12)
Eglin Air Force Base
Florida 32542

AFETR Technical Library
(ETV, MU-135)
Patrick AFB, Florida 32925

Atmospheric Sciences Office
Atmospheric Sciences Laboratory
White Sands Missile Range
New Mexico 88002

ADTC (ADBPB-12)
Eglin AFB
Florida 32542

Case Institute of Technology
Engineering Division
University Circle
Cleveland, Ohio 44106

AULIT-9663
Maxwell AFB
Alabama 36112

Commanding Officer
Naval Weapons Center
Corona Laboratories
Attn: Library
Corona, California 91720

Commander
U. S. Naval Missile Center
Point Mugu, California 93041

Deputy for Research and Engineering
(AMSRD-DRE)
U. S. Army Weapons Command
Rock Island Arsenal
Rock Island, Illinois 61201

Hallmark Associates
P. O. Box 2376
Fullerton, California 92633

Carnegie Institute of Technology
Electrical Engineering Dept.
Pittsburg, Pa. 15213

Central Intelligence Agency
Attn: OCR/DD Publications
Washington, D. C. 20505

Dr. G. M. Janney, AMSEL-HL-NVOR
Night Vision Laboratory, USAECOM
Fort Belvoir, Virginia 22060

Director, Electronic Programs
Department of the Navy
Washington, D. C. 20360
Attn: Code 427 (3)

Commandant
U. S. Army and General Staff College
Attn: **Acquisitions**, Lib. Div.
Fort Leavenworth, Kansas 66370

Commander (ADL)
Naval Air Development **Center**
Johnsville,
Warminster, Pa. 18974

Technical Director (SMUFA-A2000-107-1)
Frankford Arsenal
Philadelphia, Pa. 19137

Commandant
U. S. Army Air Defense School
Attn: Missile Sciences Div. C & S Dept.
P. O. Box 9390
Fort Bliss, Texas 79916

U. S. Army Mobility Equipment Research and Development Center
Attn: Technical Document Center, Bldg 315
Fort Belvoir, Virginia 22060

Commanding General
Attn: **STEWS-RR-L,** Technical Library
White Sands Missile Range
New Mexico 88002 (2)

Commanding General
U. S. Army Electronics Command
Fort Monmouth, New Jersey 07703

ATTN: AMSEL-SC
HL-P-2(Mr. D. Hamata)
HL-EM (Dr. Schick/
RD-GF Hieslmaier)
RD-MT
XL-D
XL-E
XL-C
XL-S (Dr. R. Buser)
HL-CT-DD
HL-CT-R
VL-PD(Dr. R. J. Niemela)
HL-CT-L (Dr. W. S.
HL-CT-O McAfee)
HL-CT-I
HL-CT-A
NL-D
NL-A
NL-P
NL-R(Mr. R. Kulinyi)
NL-S
KL-D
KL-E
KL-S(Dr. H. Jacobs)
KL-T
VL-D
WL-D

Commanding General
U. S. Army Material Command
Attn: AMCRD-TP
Washington, D. C. 20315

Commanding General
U. S. Army Missile Command
Attn: Technical Library AMSMI-RLH
Redstone Arsenal, Alabama 35809

Commanding Officer
Naval Avionics Facility
Indianapolis, Indiana 46241

Commanding Officer
Naval Ordnance Laboratory
White Oak, Maryland 21502 (2)
Attn: Librarian

Commander (Code 753)
Naval Weapons Center
China Lake, California 93555
Attn: Technical Library

Commanding Officer
Naval Training Device Center
Orlando, Florida 32813

Deputy Director and Chief Scientist
Office of Naval Research Branch Office
1030 East Green Street
Pasadena, California 91101

Commanding Officer
Office of Naval Research Branch Office
219 South Dearborn Street
Chicago, Illinois 60604

Commanding Officer
Office of Naval Research Branch Office
495 Summer Street
Boston, Massachusetts 02210

U. S. Post Office Department
Library - Room 6012
12th & Pennsylvania Ave., N.W
Washington, D. C. 20260

Commanding Officer
Office of Naval Research Branch Office
Box 39, **FPO**
New York, New York 09510 (2)

Project Manager
Common Positioning and Navigation Systems
Attn: Harold M. Bahr (AMCPM-NS-TM)
Building 83
U. S. Army Electronics Command
Fort Monmouth, New Jersey 07703

Commanding Officer
U. S. Army Electronics R & D Activity
White Sands Missile Range
New Mexico 88002

Director of Faculty Research
Department of the Air Force
USAF Academy
Colorado Springs, Colorado 80840

Richard O. Ulsh (CRDARD-IPO)
U. S. Army Research Office (Durham)
Box CM, Duke Station
Durham, North Carolina 27706

Commanding General
U. S. Army Strategic Comm. Command
Attn: SCC-CD-SAE
Fort Huachuca, Arizona 85613

Commanding Officer
Harry Diamond Laboratories
Attn: Dr. Bernhold Altman (AMXDO-TI)
Connecticut Avenue and Van Ness St. NW
Washington, D. C. 20438

Commanding Officer
Human Engineering Laboratories
Aberdeen Proving Ground
Maryland 21005

Commanding Officer
U. S. Army Ballistics Research Lab
Attn: **AMXRD-BAT**
Aberdeen Proving Ground
Aberdeen, Maryland 21005

Director, USAF Project RAND
Via: Air Force Liaison Office
The RAND Corporation
1700 Main Street
Santa Monica, California 90406
Attn: Library D

Director
U. S. Army Engineer Geodesy, Intelligence and Mapping Research and Development Agency
Fort Belvoir, Virginia 22060

Dr. G. M. R. Winkler
Director, Time Service Division
U. S. Naval Observatory
Washington, D. C. 20390

Commander, U.S. Naval Security Group Com
Attn: G43
3801 Nebraska Avenue
Washington, D. C. 20390

Division of Engineering and Applied Physics
130 Pierce Hall
Harvard University
Cambridge, Massachusetts 02138

Hq. BSD (ESTI)
L. G. Hanscom Field
Bedford, Mass. 01731 (2)

European Office of Aerospace Research
APO
New York 09667

Prof. J. J. D'Azzo
Dept. of Electrical Engineering
Air Force Institute of Technology
Wright-Patterson AFB, Ohio 45433

Lincoln Laboratory
Massachusetts Institute of Technology
Lexington, Mass. 02173

Professor Nicholas George
California Institute of Technology
Pasadena, California 91109

Dr. John C. Hancock, **Head**
School of Electrical Engineering
Purdue University
Lafayette, Indiana 47907

Dr. H. Harrison, Code RRE
Chief, Electrophysics Branch
NASA
Washington, D. C. 20546

Head, Technical Services Division
Naval Intelligence Service Hqs
4600 North Fairfax Drive
Arlington, Virginia 22203

Headquarters
Defense Communications Agency (340)
Washington, D. C. 20305

Dr. L. M. Hollingsworth
ASCRL (CRN)
L. G. Hanscom Field
Bedford, Massachusetts 01731

Hunt Library
Carnegie-Mellon University
Schenely Park
Pittsburgh, Pa. 15213

The Johns Hopkins University
Applied Physics Laboratory
8621 Georgia Avenue
Silver Spring, Maryland 20910
Attn: **Document Librarian**

Lt. Col. Robert B. Kalisch (SREE)
Chief, Electronics Division
Directorate of Engineering Sciences
Air Force Office of Scientific Research
Arlington, Virginia 22209 (5)

U. S. Army Limited War Laboratory
Attn: Technical Director
Aberdeen Proving Ground
Aberdeen, Maryland 21005

Commanding Officer
Army Materials Research
Watertown Arsenal
Watertown, Massachusetts 02172
Attn: Dr. H. Pincus

Commanding **General**
U. S. Army Security Agency
Arlington Hall Station
Arlington, Virginia 22212
Attn: IAMT-D

Commanding Officer and Director
U. S. Naval Underwater Sound Lab.
Fort Trumbull
New London, Connecticut 06840

Defense Documentation Center
Attn: **DDC-TCA**
Cameron Station
Alexandria, Virginia 22314 (20)

Det No. 6, OAR
Air Force Unit Post Office
Los Angeles, California 90045

Director
Advanced Research Projects Agency
Department of Defense
Washington, D. C. 20301

Director for Materials Sciences
Advanced Research Projects Agency
Department of Defense
Washington, D. C. 20301

Director
Columbia Radiation Laboratory
Columbia University
538 West 120th Street
New York, New York 10027

Director
Coordinated Science Laboratory
University of Illinois
Urbana, Illinois 61803

Director
Electronics Research Laboratory
University of California
Berkeley, California 94720

Director
Electronic Sciences Laboratory
University of Southern California
Los Angeles, California 90007

Director
Microwave **Physics Laboratory**
Stanford University
Stanford, California 94305

Mr. Robert O. Parker, AMSEL-RD-S
Executive Secretary, JSTAC
U. S. Army Electronics Command
Fort Monmouth, New Jersey 07703

Director
National Security Agency
Fort George G. Meade
Maryland 20755
Attn: TDL

Director, Naval Research Laboratory
Technical Information Officer
Washington, D. C. 20390
Attn: **Code 2627** (6)
Dr. W. C. Hall, **Code 7000** (1)
Dr. A. D. **Brodzinsky,** Supt. (1)

Director
Research **Laboratory of Electronics**
Massachusetts Institute of Technology
Cambridge, Massachusetts 02139

Director
Stanford Electronics Laboratories
Stanford University
Stanford, California 94305

Hqs USAF (AFRDDD)
The Pentagon
Washington, D. C. 20330

Illinois Institute of Technology
Dept. of Electrical Engineering
Chicago, Illinois 60616

Los Alamos Scientific Laboratory
Attn: Reports Library
P. O. Box 1663
Los Alamos, New Mexico 87544

Commander
U. S. Naval Electronics Laboratory Center
San Diego, California 92152 (2)
Attn: Library

The University of Arizona
Dept. of Electrical Engineering
Tucson, Arizona 85721

Dr. L. B. Mirman
AFSC (SCT)
Andrews Air Force Base
Maryland 20331

Director, Aerospace Mechanics Div
Frank J. Seiler Research Laboratory
U. S. Air Force Academy
Colorado Springs, Colorado 80912

Dr. G. J. Murphy
The Technological Institute
Northwestern University
Evanston, Illinois 60201

Director
Air Force Avionics Laboratory
Wright-Patterson AFB, Ohio 45433

NASA Lewis Research Center
Attn: Library
21000 Brookpark Road
Cleveland, Ohio 44135

Dr. Robert E. Fontana
Systems Research Laboratories Inc.
7001 Indian Ripple Road
Dayton, Ohio 45440

Nuclear Instrumentation Group
Bldg. 29, Room 101
Lawrence Radiation Laboratory
University of California
Berkeley, California 94720

Sylvania Electronic Systems
Applied Research Laboratory
Attn: Documents Librarian
40 Sylvan Road
Waltham, Mass. 02154

Naval Air Systems Command
AIR 01
Washington, D. C. 20360 (2)

Naval Electronics Systems Command
ELEX 03, Rm. 2046 Munitions Bldg
Dept. of the Navy
Washington, D. C. 20360 (2)

Utah State University
Dept. of Electrical Engineering
Logan, Utah 84321

Naval Ship Systems Command
SHIP 031
Washington, D. C. 20360

Naval Ship Systems Command
SHIP 031
Washington, D. C. 20360

New York University
College of Engineering
New York, New York 10019

Dr. H. V. Noble (CAVT)
Air Force Avionics Laboratory
Wright-Patterson AFB, Ohio 45433

Office of Deputy Director
(Research and Information Rm. 3D1037)
Department of Defense
The Pentagon
Washington, D. C. 20301

Polytechnic Institute of Brooklyn
55 Johnson Street
Brooklyn, New York 11201
Attn: Mr. Jerome Fox
Research Coordinator

Rome Air Development Center
Griffiss AFB, New York 13440
Attn: Documents Library (EMTLD)

Raytheon Co.
Bedford, Mass. 01730
Attn: Librarian

AFSC (SCTSE)
Andrews Air Force Base
Maryland 20331

Dr. A. A. Dougal
Asst. Director of Research
Office of Defense Res. and Eng.
Department of Defense
Washington, D. C. 20301

Union Carbide Corporation
Electronic Division
P. O. Box 1205
Mountain View, California 94041

Dr. H. Robl, Deputy Chief Scientist
U. S. Army Research Office (Durham)
Box CM, Duke Station
Durham, North Carolina 27706

Dr. Sheldon J. Wellen
Electronics Properties Information Center
Hughes Aircraft Company
Mail Station E-1125
Culver City, California 90230

School of Engineering Sciences
Arizona State University
Tempe, Arizona 85281

Hqs. SAMSO (SMTTA/Lt. Nelson)
AF Unit Post Office
Los Angeles, California 90045

Raytheon Company
Research Division Library
28 Seyon Street
Waltham, Mass. 02154

USAFSAM (EMKOR)
Brooks Air Force Base
Texas 78235

Syracuse University
Department of Electrical Engineering
Syracuse, New York 13210

Government Publications Section
University of California
Santa Barbara, California 93106
Attn: Library

Engineering and Math. Sciences Library
University of California at L. A.
405 Hilgard Avenue
Los Angeles, California 90024

Prof. Joseph E. Rowe, Chairman
University of Michigan
Electrical Engineering Department
Ann Arbor, Michigan 48104

U. S. Army Munitions Command
Attn: Technical Information Branch
Picatinny Arsenal, SMUFA-VAS
Dover, New Jersey 07801

U. S. Army Research Office
Physical & Engineering Sciences Div.
1045 Columbia Pike
Arlington, Virginia 22204

Dr. A. D. Schnitzler, **AMSEL-HL-NVII**
Night Vision Laboratory, USAECOM
Fort Belvoir, Virginia 22060

Department of Electrical Engineering
Texas Technological College
Lubbock, Texas 79409

U. S. Naval Weapons Laboratory
Dahlgren, Virginia 22448

Hq. USAF (AFRDSD)
The Pentagon
Washington, D. C. 20330

Director
The Walter Reed Institute of Research
Walter Reed Medical Center
Washington, D. C. 20014

Missile Electronic Warfare
Technical Area, AMSEL-WT-MT
White Sands Missile Range
New Mexico 88002

The University of Iowa
The University Libraries
Iowa City, Iowa 52240

Lenkurt Electric Co. Inc.
1105 County Road
San Carlos, California 94070
Attn: Mr. E. K. Peterson

Yale University
Engineering Department
New Haven, Connecticut 06520

Philco-Ford Corporation
Communications and Electronics Div
Union Meeting and Jolly Roads
Blue Bell, Pa. 19422

Dr. Leo Young
Stanford Research Institute
Menlo Park, California 94025

Hq. AMD (AMR)
Brooks Air Force Base
Texas 78235

Morton M. Pavane, Chief
AFSC Scientific & Technical Liaison Office
4th Federal Plaza, Rm. 1313
New York, New York 10007

Library (Code 2124)
U. S. Navy Post Graduate School
Monterey, California 93940
Attn: Technical Report Section

Director
Electronics Research Center
University of Texas at Austin
Austin, Texas 78712

Mr. H. E. Webb (RMIIB)
Rome Air Development Center
Griffiss Air Force Base
New York 13440

Col. E. P. Quines, Jr.
ACDA/PO
1901 Pennsylvania Ave., N.W.
Washington, D.C. 20451

Mr. Billy Locke
Technical Advisor, Requirements
USAF Security Service
Kelly Air Force Base, Texas 78241

Weapons Systems Evaluation Group
Attn: Colonel **Blaine O. Vogt**
400 Army-Navy Drive
Arlington, Virginia 22202

Hq. USAF (AIRDDG)
The Pentagon
Washington, D. C. 20301

W. A. Eberspacher, Assoc. Head
Systems Integration Division
Code 5560A, Box 15
Naval Missile Center
Point Mugu, California 93041

Glen A. Myers (Code 52Mv)
Assoc. Prof. of Electrical Engineering
Naval Postgraduate School
Monterey, California 93940

Mr. Norman J. Field, AMSEL-RD-S
Chief, Office of Science and Technology
R and D Directorate
U. S. Army Electronics Command
Fort Monmouth, New Jersey 07703

Redstone Scientific Information Center
Attn: Chief, Document Section
U. S. Army Missile Command
Redstone Arsenal, Alabama 35809

Federal Aviation Administration
Attn: Admin Beds Div (MS-110)
800 Independence Avenue, S W
Washington, D. C. 20590

Mr. M. Zane Thornton, Chief
Network Engineering, Communications and Operations Branch
Lister Hill National Center for Biomedical Communications
8600 Rockville Pike
Bethesda, Maryland 20014

Unclassified

Security Classification

DOCUMENT CONTROL DATA - R & D

(Security classification of title, body of abstract and indexing annotation must be entered when the overall report is classified)

1. ORIGINATING ACTIVITY *(Corporate author)*

Division of Engineering and Applied Physics
Harvard University
Cambridge, Mass. 02138

2a. REPORT SECURITY CLASSIFICATION

Unclassified

2b. GROUP

3. REPORT TITLE

QUALITATIVE APPLICATION OF A RESULT IN CONTROL THEORY TO PROBLEMS OF ECONOMIC GROWTH

4. DESCRIPTIVE NOTES *(Type of report and inclusive dates)*

Interim technical report

5. AUTHOR(S) *(First name, middle initial, last name)*

Milind M. Lele, David H. Jacobson, and James L. McCabe

6. REPORT DATE

December 1969

7a. TOTAL NO. OF PAGES

33

7b. NO. OF REFS

16

8a. CONTRACT OR GRANT NO.

N00014-67-A-0298-0006 and NASA Grant NGR 22-007-068

b. PROJECT NO.

c.

d.

9a. ORIGINATOR'S REPORT NUMBER(S)

Technical Report No. 602

9b. OTHER REPORT NO(S) *(Any other numbers that may be assigned this report)*

10. DISTRIBUTION STATEMENT

This document has been approved for public release and sale; its distribution is unlimited. Reproduction in whole or in part is permitted by the U. S. Government.

11. SUPPLEMENTARY NOTES

12. SPONSORING MILITARY ACTIVITY

Office of Naval Research

13. ABSTRACT

Recent investigations into necessary conditions of optimality for control problems with inequality constraints on the state variables have shown that, for a specific class of problems, the optimal trajectory does not stay on the constraint boundary for non-zero intervals of time. This result permits, a priori, some insight into the structure of the optimal solution.

For certain problems in growth economics, this result is of some significance, as is shown by three examples from two different areas. The first two examples are concerned with the problem of optimal employment; interestingly enough, they indicate that, for the models used, the optimal solution is such that full employment is attained at most instantaneously and is not maintained for non-zero intervals of time. The third example is concerned with the optimal investment and foreign aid policies for an underdeveloped economy. An institutional constraint on the stock of foreign debts may be derived from the 'debt-service' ratio. It appears that, contrary to earlier results obtained from simpler models, this constraint is binding at most instantaneously along the optimal trajectory.

DD FORM 1 NOV 65 1473 (PAGE 1)

S/N 0101-807-6801

Unclassified

Security Classification

14. KEY WORDS	LINK A ROLE	LINK A WT	LINK B ROLE	LINK B WT	LINK C ROLE	LINK C WT
Economic Growth						
Optimal Employment						
Optimal Foreign Aid Allocation						
Application of Optimal Control						
State Variable Inequality Constraint						